

# 2SP0325x2Ax-CM1800DY-34S

## Preliminary Data Sheet

Compact, high-performance, plug-and-play dual-channel IGBT driver based on SCALE™-2 technology for Mitsubishi's New Mega Power Dual IGBT modules.

### Abstract

The SCALE™-2 plug-and-play driver 2SP0325x2Ax-CM1800DY-34S is a compact dual-channel intelligent gate driver designed for Mitsubishi's New Mega Power Dual (New MPD) IGBT modules CM1800DY-34S 300G and CM1800DY-34S 302G. The driver features an electrical interface (2SP0325T) or a fiber-optic interface (2SP0325V) with a built-in DC/DC power supply.

For drivers adapted to other types of high-power and high-voltage IGBT modules, refer to

[www.IGBT-Driver.com/go/plug-and-play](http://www.IGBT-Driver.com/go/plug-and-play)

### Features

- ✓ Plug-and-play solution
- ✓ For 2-level, 3-level and multilevel topologies
- ✓ Built-in DC/DC power supply
- ✓ 20-pin flat cable interface (2SP0325T)
- ✓ Fiber-optic links (2SP0325V)
- ✓ Duty cycle 0... 100%
- ✓ Dynamic Advanced Active Clamping DA<sup>2</sup>C
- ✓ IGBT short-circuit protection
- ✓ Monitoring of supply voltage
- ✓ Safe isolation to EN 50178
- ✓ UL compliant
- ✓ Lead free
- ✓ Extremely reliable; long service life
- ✓ Shortens application development time
- ✓ Suitable for CM1800DY-34S 300G and CM1800DY-34S 302G

### Applications

- ✓ Wind power converters
- ✓ AC motor control
- ✓ Power supply
- ✓ Medium voltage drives
- ✓ And many others

## Preliminary Data Sheet

### Safety Notice!

The data contained in this data sheet is intended exclusively for technically trained staff. Handling all high-voltage equipment involves risk to life. Strict compliance with the respective safety regulations is mandatory!

Any handling of electronic devices is subject to the general specifications for protecting electrostatic-sensitive devices according to international standard IEC 60747-1, Chapter IX or European standard EN 100015 (i.e. the workplace, tools, etc. must comply with these standards). Otherwise, this product may be damaged.

### Important Product Documentation

This data sheet contains only product-specific data. For a detailed description, must-read application notes and common data that apply to the whole series, please refer to "Description & Application Manual for 2SP0325T SCALE-2 IGBT Drivers" (electrical interface) or "Description & Application Manual for 2SP0325V SCALE-2 IGBT Drivers" (fiber-optic interface) on [www.IGBT-Driver.com/go/2SP0325](http://www.IGBT-Driver.com/go/2SP0325).

When applying SCALE-2 plug-and-play drivers, please note that these drivers are specifically adapted to a particular type of IGBT module. Therefore, the type designation of SCALE-2 plug-and-play drivers also includes the type designation of the corresponding IGBT module. These drivers are not valid for IGBT modules other than those specified. Incorrect use may result in failure.

### Mechanical Dimensions

Dimensions: See the relevant "Description and Application Manual"

Mounting principle: Connected to IGBT module with screws

### Fiber-Optic Interfaces

| Interface          | Remarks  | Part type #  |
|--------------------|--|--------------|
| Drive signal input | 2SP0325V, fiber-optic receiver (Notes 21, 22)    | HFBR-2522ETZ |
| Status output      | 2SP0325V, fiber-optic transmitter (Notes 21, 23) | HFBR-1522ETZ |

## Preliminary Data Sheet

### Absolute Maximum Ratings

| Parameter                       | Remarks   | Min  | Max     | Unit          |
|---------------------------------|---|------|---------|---------------|
| Supply voltage $V_{DC}$         | VDC to GND (Note 1)                                 | 0    | 16      | V             |
| Supply voltage $V_{CC}$         | VCC to GND (Note 1)                                 | 0    | 16      | V             |
| Logic input and output voltages | To GND  | -0.5 | VCC+0.5 | V             |
| SO <sub>x</sub> current         | Fault condition, total current                      |      | 20      | mA            |
| Gate peak current $I_{out}$     | Note 2  | -25  | +25     | A             |
| Average supply current $I_{DC}$ | 2SP0325T (Note 24)                                  |      | 430     | mA            |
| Average supply current $I_{DC}$ | 2SP0325V (Note 24)                                  |      | 550     | mA            |
| Output power per gate           | Note 3  |      | 2       | W             |
| Switching frequency F           |   |      | 5       | kHz           |
| Test voltage (50Hz/1min.)       | Primary to secondary (Note 19)                      |      | 5000    | $V_{AC(eff)}$ |
|                                 | Secondary to secondary (Note 19)                    |      | 4000    | $V_{AC(eff)}$ |
| DC-link voltage                 | Switching operation (Note 4)                        |      | 1200    | V             |
|                                 | Off state (Note 29)                                 |      | 1350    | V             |
| $ dv/dt $                       | Rate of change of input to output voltage (Note 20) |      | 50      | kV/ $\mu$ s   |
| Operating voltage               | Primary/secondary, secondary/secondary              |      | 1700    | $V_{peak}$    |
| Operating temperature           |   | -40  | +85     | °C            |
| Storage temperature             |   | -40  | +90     | °C            |

### Recommended Operating Conditions

| Power Supply              | Remarks                                      | Min  | Typ | Max      | Unit       |
|---------------------------|--|------|-----|----------|------------|
| Supply voltage $V_{DC}$   | To GND (Note 1)                              | 14.5 | 15  | 15.5     | V          |
| Supply voltage $V_{CC}$   | To GND (Note 1)                              | 14.5 | 15  | 15.5     | V          |
| Resistance from TB to GND | 2SP0325T, blocking time $\neq$ 0, ext. value | 128  |     | $\infty$ | k $\Omega$ |

## Preliminary Data Sheet

### Electrical Characteristics

All data refer to +25°C and  $V_{CC} = V_{DC} = 15V$  unless otherwise specified

| Power Supply                        | Remarks  | Min  | Typ  | Max  | Unit       |
|-------------------------------------|--|------|------|------|------------|
| Supply current $I_{DC}$             | 2SP0325T, without load                             |      | 32   |      | mA         |
|                                     | 2SP0325V, without load                             |      | 145  |      | mA         |
| Efficiency $\eta$                   | Internal DC/DC converter                           |      | 85   |      | %          |
| Supply current $I_{CC}$             | Without load                                       |      | 23   |      | mA         |
| Coupling capacitance $C_{io}$       | Primary side to secondary side, total, per channel |      |      |      |            |
|                                     | 2SP0325T   |      | 22   |      | pF         |
|                                     | 2SP0325V   |      | 12   |      | pF         |
| Power Supply Monitoring             | Remarks  | Min  | Typ  | Max  | Unit       |
| Supply threshold $V_{CC}$           | Primary side, clear fault                          | 11.9 | 12.6 | 13.3 | V          |
|                                     | Primary side, set fault (Note 5)                   | 11.3 | 12.0 | 12.7 | V          |
| Monitoring hysteresis               | Primary side, set/clear fault                      | 0.35 |      |      | V          |
| Supply threshold $V_{isox}-V_{eex}$ | Secondary side, clear fault                        | 12.1 | 12.6 | 13.1 | V          |
|                                     | Secondary side, set fault (Note 26)                | 11.5 | 12.0 | 12.5 | V          |
| Monitoring hysteresis               | Secondary side, set/clear fault                    | 0.35 |      |      | V          |
| Supply threshold $V_{eex}-V_{COMx}$ | Secondary side, clear fault                        | 5    | 5.15 | 5.3  | V          |
|                                     | Secondary side, set fault (Note 26)                | 4.7  | 4.85 | 5    | V          |
| Monitoring hysteresis               | Secondary side, set/clear fault                    | 0.15 |      |      | V          |
| Logic Inputs and Outputs            | Remarks  | Min  | Typ  | Max  | Unit       |
| Input impedance                     | 2SP0325T, $V(INx) = 15V$ (Note 6)                  | 4.7  | 4.8  | 4.9  | k $\Omega$ |
| Turn-on threshold                   | 2SP0325T, $V(INx)$ (Note 7)                        |      | 8.8  |      | V          |
| Turn-off threshold                  | 2SP0325T, $V(INx)$ (Note 7)                        |      | 4.5  |      | V          |
| SOx output voltage                  | Fault condition, $I(SOx) < 8mA$                    |      |      | 0.7  | V          |
| Short-circuit Protection            | Remarks  | Min  | Typ  | Max  | Unit       |
| $V_{CE}$ -monitoring threshold      | Between auxiliary terminals                        |      | 10.2 |      | V          |
| Response time                       | Half-bridge short circuit,                         |      |      |      |            |
|                                     | DC-link voltage > 800V (Note 8)                    |      | 5.8  |      | $\mu s$    |
| Delay in IGBT turn-off $T_{cshd}$   | After the response time (Note 9)                   |      | 0.1  |      | $\mu s$    |
| Blocking time                       | 2SP0325T, after fault (Note 10)                    |      | 90   |      | ms         |

## Preliminary Data Sheet

| Timing Characteristics                  | Remarks                               | Min            | Typ        | Max  | Unit       |
|---|---------------------------------------|----------------|------------|------|------------|
| Turn-on delay $T_{d(on)}$               | 2SP0325T (Note 11)                    |                | 80         |      | ns         |
| Turn-off delay $T_{d(off)}$             | 2SP0325T (Note 11)                    |                | 65         |      | ns         |
| Jitter of turn-on delay                 | 2SP0325T (Note 28)                    |                | ±2         |      | ns         |
| Jitter of turn-off delay                | 2SP0325T (Note 28)                    |                | ±2         |      | ns         |
| Turn-on delay $T_{d(on)}$               | 2SP0325V (Note 12)                    |                | 120        |      | ns         |
| Turn-off delay $T_{d(off)}$             | 2SP0325V (Note 12)                    |                | 100        |      | ns         |
| Output rise time $T_{r(out)}$           | $G_x$ to $E_x$ (Note 13)              |                | 25         |      | ns         |
| Output fall time $T_{f(out)}$           | $G_x$ to $E_x$ (Note 13)              |                | 17         |      | ns         |
| Dead time between outputs               | 2SP0325T, half-bridge mode (Note 30)  |                | 3          |      | µs         |
| Jitter of dead time                     | 2SP0325T, half-bridge mode            |                | ±100       |      | ns         |
| Transmission delay of fault state       | 2SP0325T (Note 14)                    |                | 450        |      | ns         |
| Transmission delay of fault state       | 2SP0325V (Note 25)                    |                | 90         |      | ns         |
| Delay to clear fault state              | 2SP0325V (Note 15)                    |                | 8          |      | µs         |
| Acknowledge delay time $T_{d(ack)}$     | 2SP0325V (Note 16)                    |                | 200        |      | ns         |
| Acknowledge pulse width $T_{(ack,on)}$  | 2SP0325V (at turn-on, on host side)   | 400            | 600        | 1050 | ns         |
| Acknowledge pulse width $T_{(ack,off)}$ | 2SP0325V (at turn-off, on host side)  | 400            | 750        | 1150 | ns         |
| Outputs                                 | Remarks                               | Min            | Typ        | Max  | Unit       |
| Turn-on gate resistor $R_{g(on)}$       | Note 17                               |                | 0          |      | Ω          |
| Turn-off gate resistor $R_{g(off)}$     | Note 17                               |                | 2          |      | Ω          |
| Gate voltage at turn-on                 |                                       |                | 15         |      | V          |
| Gate-voltage at turn-off                | 2SP0325T/2SP0325V                     |                |            |      |            |
|   | F = 0kHz                              |                | -10.2/-9.9 |      | V          |
|   | F = 5kHz                              |                | -9.7/-9.3  |      | V          |
| Gate resistance to COMx                 |                                       |                | 4.7        |      | kΩ         |
| dv/dt Feedback                          | Remarks                               | Implementation |            |      |            |
| dv/dt feedback                          | Note 18                               |                | Yes        |      |            |
| Electrical Isolation                    | Remarks                               | Min            | Typ        | Max  | Unit       |
| Test voltage (50Hz/1s)                  | Primary to secondary side (Note 19)   | 5000           | 5050       | 5100 | $V_{eff}$  |
|   | Secondary to secondary side (Note 19) | 4000           | 4050       | 4100 | $V_{eff}$  |
| Partial discharge extinction volt.      | Primary to secondary side (Note 27)   | 1768           |            |      | $V_{peak}$ |
|   | Secondary to secondary side (Note 27) | 1700           |            |      | $V_{peak}$ |
| Creepage distance                       | Primary to secondary side             | 12.5           |            |      | mm         |
|   | Secondary to secondary side           | 6.5            |            |      | mm         |
| Clearance distance                      | Primary to secondary side             | 12.5           |            |      | mm         |
|   | Secondary to secondary side           | 6.5            |            |      | mm         |

---

## Preliminary Data Sheet

### Footnotes to the Key Data

- 1) Both supply voltages  $V_{DC}$  and  $V_{CC}$  should be applied in parallel.
- 2) The gate current is limited by the gate resistors located on the driver and the internal gate resistance of the IGBT module.
- 3) If the specified value is exceeded, this indicates a driver overload. It should be noted that the driver is not protected against overload.
- 4) This limit is due to active clamping. Refer to "Description & Application Manual for 2SP0325T SCALE-2 IGBT Drivers" (electrical interface) or "Description & Application Manual for 2SP0325V SCALE-2 IGBT Drivers" (fiber-optic interface).
- 5) Undervoltage monitoring of the primary-side supply voltage ( $V_{CC}$  to GND). If the voltage drops below this limit, a fault is transmitted to the corresponding output(s) (2SP0325T and 2SP0325V) and the IGBTs are switched off (only 2SP0325T).
- 6) The input impedance can be modified (customer-specific solution).
- 7) Turn-on and turn-off threshold values can be modified (customer-specific solution).
- 8) The pulse width resulting from the direct output of the gate drive unit for half-bridge short circuits (excluding the delay of the gate resistors) is the sum of the response time plus the delay to IGBT turn-off. The short-circuit time may vary depending on the exact short-circuit conditions. Note that Mitsubishi's short-circuit SOA CMH-10028 does not allow short-circuit inductances smaller than 10uH for external short circuits with CM1800DY-34S 300G, and that Mitsubishi's short-circuit SOA CMH-10029 does not allow short-circuit inductances smaller than 5uH for external short circuits with CM1800DY-34S 302G.
- 9) The turn-off event of the IGBT is delayed by the specified time after the response time.
- 10) Factory set value. The blocking time can be reduced with an external resistor. Refer to "Description & Application Manual for 2SP0325T SCALE-2 IGBT Drivers".
- 11) Measured from the transition of the turn-on or turn-off command at the driver input to direct output of the gate drive unit (excluding the delay of the gate resistors).
- 12) Including the delay of the external fiber-optic links. Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the direct output of the gate drive unit (excluding the delay of the gate resistors).
- 13) Output rise and fall times are measured between 10% and 90% of the nominal output swing with an output load of  $1\Omega$  (rise time)/ $2\Omega$  (fall time) and 660nF. The values are given for the driver side of the gate resistors.
- 14) Transmission delay of the fault state from the secondary side to the primary status outputs.
- 15) Measured on the host side. The fault status on the secondary side is automatically reset after the specified time.
- 16) Including the delay of the external fiber-optic links. Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the transition of the acknowledge signal at the optical receiver on the host controller side.
- 17) The gate resistors can be leaded or surface mounted. CONCEPT reserves the right to determine which type will be used. Typically, higher quantities will be produced with SMD resistors and small quantities with leaded resistors.
- 18) With "Yes", a  $dv/dt$  feedback reduces the rate of rise of the collector-emitter voltage of the IGBTs at turn-off. For more information, refer to the "Description & Application Manual for 2SP0325T SCALE-2 IGBT Drivers" (electrical interface), or the "Description & Application Manual for 2SP0325V SCALE-2 IGBT Drivers" (fiber-optic interface). With "No", no  $dv/dt$  feedback is implemented.
- 19) HiPot testing (= dielectric testing) must generally be restricted to suitable components. This gate driver is suited for HiPot testing. Nevertheless, it is strongly recommended to limit the testing time to 1s slots as stipulated by EN 50178. Excessive HiPot testing at voltages much higher than  $1200V_{AC(eff)}$  may lead to insulation degradation. No degradation has been observed over 1min. testing at  $5000V_{AC(eff)}$ . Every production sample shipped to customers has undergone 100% testing at the given value for 1s.
- 20) This specification guarantees that the drive information will be transferred reliably even at a high DC-link voltage and with ultra-fast switching operations.

## Preliminary Data Sheet

- 21) The transceivers required on the host controller side are not supplied with the gate driver. It is recommended to use the same types as used in the gate driver. For product information refer to [www.IGBT-Driver.com/go/fiberoptics](http://www.IGBT-Driver.com/go/fiberoptics)
- 22) The recommended transmitter current at the host controller is 20mA. A higher current may increase jitter or delay at turn-off.
- 23) The typical transmitter current at the gate driver is 18mA. In case of supply undervoltage, the minimum transmitter current at the gate driver is 12mA: this is suitable for adequate plastic optical fibers with a length of more than 10 meters.
- 24) If the specified value is exceeded, this indicates a driver overload. It should be noted that the driver is not protected against overload.
- 25) Delay of external fiber-optic links. Measured from the driver secondary side (ASIC output) to the optical receiver on the host controller.
- 26) Undervoltage monitoring of the secondary-side supply voltage (Visox to Veex and Veex to COMx which correspond with the approximate turn-on and turn-off gate-emitter voltages). If the corresponding voltage drops below this limit, the IGBT is switched off and a fault is transmitted to the corresponding output.
- 27) Partial discharge measurement is performed in accordance with IEC 60270 and isolation coordination specified in EN 50178. The partial discharge extinction voltage between primary and either secondary side is coordinated for safe isolation to EN 50178.
- 28) Jitter measurements are performed with input signals INx switching between 0V and 15V referred to GND, with a corresponding rise time and fall time of 8ns.
- 29) Due to the Dynamic Active Advanced Clamping Function (DA<sup>2</sup>C) implemented on the driver, the DC-link voltage can be increased in the off-state condition (e.g. after emergency shut-down). This value is only valid when the IGBTs are in the off state (not switching). The time during which the voltage can be applied should be limited to short periods (< 60 seconds). Refer to "Description & Application Manual for 2SP0325T SCALE-2 IGBT Drivers" (electrical interface) or "Description & Application Manual for 2SP0325V SCALE-2 IGBT Drivers" (fiber-optic interface).
- 30) Note that the dead time may vary from sample to sample. A tolerance of approximately ±20% may be expected. If higher timing precisions are required, CONCEPT recommends using direct mode and generating the dead time externally.

### Legal Disclaimer

This data sheet specifies devices but cannot promise to deliver any specific characteristics. No warranty or guarantee is given – either expressly or implicitly – regarding delivery, performance or suitability.

CT-Concept Technologie GmbH reserves the right to make modifications to its technical data and product specifications at any time without prior notice. The general terms and conditions of delivery of CT-Concept Technologie GmbH apply.

## Preliminary Data Sheet

### Ordering Information

The general terms and conditions of delivery of CT-Concept Technologie GmbH apply.

| Interface                           | CONCEPT Driver Type #    | Related IGBT |
|-------------------------------------|--------------------------|--------------|
| Electrical Interface                | 2SP0325T2A1-CM1800DY-34S | CM1800DY-34S |
| Fiber-Optic Interface <sup>1)</sup> | 2SP0325V2A1-CM1800DY-34S | CM1800DY-34S |

1) Fiber-optic interface with versatile link (HFBR-2522ETZ and HFBR-1522ETZ)  
 See "Description & Application Manual for 2SP0325V SCALE-2 IGBT Drivers"

Product home page: [www.IGBT-Driver.com/go/2SP0325](http://www.IGBT-Driver.com/go/2SP0325)

Refer to [www.IGBT-Driver.com/go/nomenclature](http://www.IGBT-Driver.com/go/nomenclature) for information on driver nomenclature

### Information about Other Products

For other drivers, evaluation systems product documentation and application support

Please click: [www.IGBT-Driver.com](http://www.IGBT-Driver.com)

### Manufacturer

CT-Concept Technologie GmbH  
 A Power Integrations Company  
 Johann-Renfer-Strasse 15  
 2504 Biel-Bienne  
 Switzerland

Phone +41 - 32 - 344 47 47  
 Fax +41 - 32 - 344 47 40

E-mail [Info@IGBT-Driver.com](mailto:Info@IGBT-Driver.com)  
 Internet [www.IGBT-Driver.com](http://www.IGBT-Driver.com)

© 2012...2014 CT-Concept Technologie GmbH - Switzerland.

All rights reserved.

We reserve the right to make any technical modifications without prior notice.

Version 2.0 from 2016-05-20