

Internet Office 120V 650VA 330W Standby UPS, Compact Desktop, USB Monitoring and Charging

MODEL NUMBER: INTERNET650U1









Compact desktop UPS provides basic battery backup and protects your computer and peripherals against surges and other power threats.

Features

Compact Desktop 650VA/330W Battery Backup for PCs, Home Theater and Digital SignageThis 120V UPS system provides reliable battery backup and AC power protection against blackouts, brownouts, overvoltages, surges and line noise that can damage valuable electronics or destroy data. The eight-outlet 120V battery backup is ideal protection for your home office, media center or professional kiosk, security and small-business phone applications, including computers, routers, printers, HDTVs, Bluray players, game consoles, ATMs, security systems and digital signage equipment.

Allows Time to Back Up Critical Files During a BlackoutBackup support allows you to work through short power failures, and gives you enough time to safely save files and shut down your system in case of a prolonged blackout. Backup time varies according to load, but the INTERNET650U1 should keep an energy-efficient desktop computer with small LCD monitor powered as long as 17 minutes. During normal operation, incoming utility power keeps the replaceable internal battery fully charged, so backup power will always be available.

HID-Compliant USB Port Allows for Automatic Saves and ShutdownsThis port connects the INTERNET650U1 to a computer running Tripp Lite's free downloadable PowerAlert® software to enable safe unattended file saves and system shutdown in case of a prolonged power failure. USB cable is included. The UPS works with Windows, Mac and Linux operating systems.

Connects Your Equipment to 8 Protected NEMA 5-15R Outlets Four 5-15R outlets provide both battery backup and surge protection to your computer, monitor and other crucial components. The other four are surge-protected only for printers, scanners and other non-essential equipment. A 316-joule surge suppression rating protects connected components from the harmful effects of power surges. Two outlets are spaced apart from the others to accommodate bulky transformers. RJ45 jacks protect a standard dial-up/DSL phone connection or 10Base-T Ethernet line connection from data line surges.

Charges Mobile Devices, Including Smartphones and Tablets A USB charging port delivers up to 5V 1A maximum charge current for keeping your phone, MP3 player and other USB-compatible device at 100% capacity.

Combats Electromagnetic Interference That Can Harm Equipment Various electromagnetic and radio sources found in virtually every home and business can cause disruptive interference on the AC line.

Highlights

- Protects equipment against blackouts, brownouts, overvoltages, surges and line noise
- 8 NEMA 5-15R outlets provide power to PC, home theater or networking equipment
- USB charging port delivers 5V 1A for charging smartphones, tablets and other devices
- High >98% efficiency reduces BTU emissions, saves power and lowers energy costs
- HID-compliant USB port connects to computer to enable automatic file saves and shutdowns

Applications

- Protect your PC and other sensitive electronics against power surges, line noise, brownouts, overvoltages and blackouts
- Operate essential equipment during short-term power outages using battery backup power
- Shut down PCs and peripherals without data loss during longterm power outages

Package Includes

- INTERNET650U1 120V 650VA 330W Standby UPS with 8 Outlets
- USB cable
- Owner's manual



Known as EMI (electromagnetic interference) and RFI (radio frequency interference), this line noise is a common cause of performance problems and can lead to incremental hardware damage, data corruption and audio/video transmission problems. The INTERNET650U1 incorporates technology that filters out disruptive line noise so that it won't affect your equipment.

Diagnostic LED and Audible Alarm Keep You InformedFront-panel green LED indicates line/battery mode status, overloads and low/replace battery alert. A home-friendly alarm stays silent in AC and battery modes, except to warn you of a low battery or fault condition.

High Line-Mode Efficiency Saves Energy and Cuts CostsA high >98% line mode efficiency rating reduces BTU emissions, energy consumption and, ultimately, your energy costs.

Compact Housing for Convenient Installation Almost AnywhereThe space-saving housing fits easily on a desktop, shelf or anywhere else convenient to your workstation. Keyhole mounting tabs allows easy wall installation. The five-foot power cord with NEMA 5-15P plug connects to a standard AC outlet.

Specifications

OVERVIEW		
UPC Code	037332211057	
UPS Type	Standby	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	6A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
Input Circuit Breakers	7A	
UPS Input Cord Length (ft.)	5	
UPS Input Cord Length (m)	1.5	
Recommended Electrical Service	15A 120V	
ОИТРИТ		
Output Capacity (VA)	650	
Output Capacity (kVA)	0.65	
Output Capacity (Watts)	330	
Output Capacity (kW)	0.33	
Nominal Voltage Details	120v nominal output in battery mode	
Frequency Compatibility	50 / 60 Hz	
Output Voltage Regulation (Battery Mode)	±5%	
UPS Output Receptacles (Surge Suppression Only)	4 UPS outlets, 4 surge-only outlets	



Hot-Swap PDU options PDUB15 (2U / 8 5-15R outlets) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery mode operation SURGE / Noise Suppression UPS AC Suppression Joule Rating 316 UPS AC Suppression Joule Rating Instantaneous Instantaneous			
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Upstantageous Instantageous			
Nominal Output Voltage(s) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating UPS AC Suppression Sesponse Instantaneous			
Supported Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating UPS AC Suppression Joule Rating Instantance I			
Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instanceous			
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 1 min. (330W) Runtime Half Load (min.) 4.5 min. (165W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included atteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
Runtime Full Load (min.) Runtime Half Load (min.) Runtime Half Load (min.) Expandable Runtime No DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous	BATTERY		
Runtime Half Load (min.) Expandable Runtime No DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous			
Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) 6.5 hours from 10% to 90% Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous			
Battery Recharge Rate (Included Batteries) Battery Access Battery access door (see manual) Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 1 Instantaneous Instantaneous			
Battery Access Battery Access Battery Access Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous			
Battery Replacement Description Replaceable batteries USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
USER INTERFACE, ALERTS & CONTROLS Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
Switches Power switch enables UPS on / off control Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
Audible Alarm Alarm reports low-battery, fault, overload and replace battery conditions LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous	USER INTERFACE, ALERTS & CONTROLS		
LED Indicators Status LED reports off / on power status and battery mode operation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous			
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
UPS AC Suppression Joule Rating 316 UPS AC Suppression Response Instantaneous			
UPS AC Suppression Response Instantaneous	SURGE / NOISE SUPPRESSION		
UPS Dataline Suppression 1 line TEL/DSL or Ethernet			
EMI / RFI AC Noise Suppression Yes			
PHYSICAL			
Primary Form Factor Desktop			
Included Mounting Accessory Description Wallmount installation supported using keyhole mounting tabs			
Installation Form Factors Supported with Included Accessories Tower; Ultra-compact desktop; Wallmount	-		
Primary UPS Depth (mm) 185			
Primary UPS Height (mm) 105			



Primary UPS Width (mm)	110
Shipping Dimensions (hwd / in.)	7.10 x 5.50 x 10.90
Shipping Weight (kg)	2.22
UPS Housing Material	ABS
UPS Power Module Dimensions (hwd, in.)	4.13 x 4.33 x 7.28
UPS Power Module Weight (kg)	1.80
UPS Power Module Weight (lbs.)	3.96
Unit Weight (lbs.)	3.960
Unit Weight (kg)	1.80
ENVIRONMENTAL	
Operating Temperature Range	32° to 104°F (0° to 40°C)
Storage Temperature Range	5° to 113°F (-15° to 45°C)
Relative Humidity	Up to 90%, non-condensing
AC Mode BTU / Hr. (Full Load)	13.07
AC Mode Efficiency Rating (100% Load)	>98%
COMMUNICATIONS	
PowerAlert Software	For local monitoring via the UPS's built-in USB communications port, download PowerAlert software at https://tripplite.eaton.com/products/power-alert
Communications Cable	USB interface cable included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network Management Card Description	Network management not supported
Communications Interface	USB (HID enabled)
LINE / BATTERY TRANSFER	
Transfer Time	6 milliseconds (typical) / 10 milliseconds (max)
Low Voltage Transfer to Battery Power (Setpoint)	95V
High Voltage Transfer to Battery Power (Setpoint)	145V
FEATURES & SPECIFICATIONS	
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features	Surge/noise protection
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS



APPLICATIONS		
UPS Applications	Computer/Peripherals; Retail/Point of Sale; Hospitality	
STANDARDS & COMPLIANCE		
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778	
Product Compliance	RoHS; FCC Part 15 Class B (USA)	
WARRANTY & SUPPORT		
Product Warranty Period (U.S. & Canada)	3-year limited warranty	
Product Warranty Period (Latin America)	3-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	3-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$100,000 Ultimate Lifetime Insurance	



© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.