

MODEL SUMMARY

An SFP+ application, defined by SFF-8431, could be an electrical-to-optical module or an electrical-to-electrical device such as a passive cable. SFP+ applications are intended to support Datacom applications. Examples of these applications are 10 Gbps Ethernet, 8.5 Gbps Fibre Channel, 10.51 Gbps Fibre Channel, 10 Gbps Ethernet with FEC and Telecom (SONET OC-192 and G.709 "OTU-2").

The SFF-8083 specification defines the SFP/SFP+ host connector. It includes both the dimensional requirements and the high-speed signal integrity requirements.

The SFF-8432 specification defines the requirements for the improved SFP+ cage and modules in order to address EMC compliance.

Further information regarding this connector product line and other related Molex SFP+ products can be found at <u>http://www.molex.com/product/sfp-plus.html</u>

Small Form-Factor Pluggable (SFP+) Stacked Multi-Port Connectors



MODEL TYPE: S-parameter	MODEL FORMAT: Touchstone (*.sNp)
MODEL FILENAME: EE-76090-001_rev2.s16p	DATA FORMAT: Real/Imaginary
MODEL BASIS: Analytical 3-D field solution	MODEL SOURCE: Ansoft HFSS version 11.1.3
BANDWIDTH: DC - 20.48 GHz	RESOLUTION: 10 MHz steps
REFERENCE: 50 ohms	NUMBER OF POINTS: 2049 (2048 + 1 DC)
NUMBER OF CHANNELS: 4 differential	NUMBER OF PORTS: 16 single-ended
CHANNEL TYPE: Coupled pairs + reference	VALIDATION: Yes
MODEL APPLICATION: Open	DATA RATE: 10.3125 Gbps

APPLICABLE PART NUMBER(S):

	Elastomeric Gasket		Metal Ga	asket
Light-pipes	Yes	Yes No Yes		No
2x1	76090	76100	76044	76064
2x2	76091	76101	76045	76065
2x4	76092	76102	76046	76066
2x5	76093	76103	76047	76067
2x6	76094	76104	76048	76068
2x8	76352			

DISCLAIMERS: Information contained in this document is simulated. Molex Incorporated does not guarantee the performance of the final product to the information provided in this document.

Molex does not represent, warrant or guarantee the accuracy of the information, expressly disclaims all warranties including the implied warranties of merchantability and fitness for particular purpose and shall not be liable for any damages whatsoever arising from use of, or inability to use, the information contained in this document or accompanying electronic file.

The user is responsible for verifying the results of their use of this information, and assumes all risk of doing or not doing so. Use of the electronic file evidences user's agreement to the above terms.

REVISION:	ECN INFORMATION: EC No: UCP2014-0167		SFP+ Stacked i-Port Connectors	5	<u>SHEET No.</u> 1 of 9
A DATE: 2009 / 4 / 3	DATE: 2009 / 4 / 3	MOLEX CONFIDE	NTIAL F	RESTRICTED	1019
DOCUMEN	NUMBER:	CREATED / REVISED BY:	CHECKED BY:	APPROV	ED BY:
E	E-76090-001	01 P. Casher R. Benson D. Dun		nham	
			TEMF	LATE FILENAME: SPM	[SIZE_A](V.1).DOC



MODEL DESCRIPTION

This model is of both the upper port and lower ports. It contains all twenty terminals in each port. However, the two ports were solver separately and then joined as a post process, so there is no modeled coupling, crosstalk, between the two. The host board thickness is 3.0mm (0.118"). A dielectric constant of 3.8 was used for the modeled material properties. It represents an application with 24 layers, 14 power/ground layers and 10 signal layers. The high-speed signals are on layer 23, which is located ~0.3mm (0.0116") from the bottom of the board. This is in order to minimize the stub effects created by the relative connection location to the vias, which support to the connector.

TERMINAL TO MODEL PORT MAPPING TABLE

Available Model Signal Paths

Port	Terminals	Input Ports	Description	Output Ports	Description
	12	1	RD-, Host Board	2	RD-, Module Board
Upper	13	3	RD+, Host Board	4	RD+, Module Board
Opper	18	5	TD+, Host Board	6	TD+, Module Board
	19	7	TD-, Host Board	8	TD-, Module Board
Lower	12	9	RD-, Host Board	10	RD-, Module Board
	13	11	RD+, Host Board	12	RD+, Module Board
	18	13	TD+, Host Board	14	TD+, Module Board
	19	15	TD-, Host Board	16	TD-, Module Board

Non-available Signal Paths

Terminals	
1,2,3,4,5,6,7,8,9,10 11,14,15,16,17,20	


- Within each port

REVISION:	ECN INFORMATION:	TITLE:	SFP+ Stacked		SHEET No.
2	EC No: UCP2014-0167		Multi-Port Connectors		
<u>DATE:</u> 2009 / 4 / 3	MOLEX CONFIDE		RESTRICTED	2 of 9	
DOCUMEN	T NUMBER:	CREATED / REVISED BY:	CHECKED BY:	APPROV	ED BY:
E	E-76090-001	P. Casher	R. Benson	Benson D. Dunham	
			TEM	LATE FILENAME: SPN	I[SIZE_A](V.1).DOC




PART ILLUSTRATIONS


Perspective



Edge Card(S) Pins 19 & 18 Pins13 & 12 Ports 8 & 6 Ports 4 & 2 Pins 12 & 13 Pins18 & 19 Ports 10 & 12 Ports 14 & 16










REFERENCE SCHEMATICS

Time Domain Schematic



Schematic Symbol

Application: Filename(s): Agilent Advanced Design System (ADS), version 2006 Update 3 EE-76090-002.(dsn, ael)

2	DATE: 2009 / 4 / 3		ESTR
	EC No: UCP2014-0167	7 Multi-Port Connectors	
REVISION:	ECN INFORMATION:	TITLE: SFP+ Stacked	
	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$		

 2
 DATE: 2009 / 4 / 3
 MULTI-PORT Connectors MULTI-PORT Connectors DATE: 2009 / 4 / 3
 5 of 9

 DOCUMENT NUMBER:
 CREATED / REVISED BY: CHECKED BY: APPROVED BY: D. Dunham
 5 of 9

 EE-76090-001
 P. Casher
 R. Benson
 D. Dunham

SHEET No.




REFERENCE RESULTS

Differential Frequency Domain

Insertion Loss

- Of assignment 1/3 to 2/4 (blue) and 9/11 to 10/12 (magenta)
- Upper port (blue), Lower port (magenta)






REFERENCE RESULTS

Differential Frequency Domain (continued)

- Near-end Crosstalk, With-in Row
 - Of Assignment 1/3 to 6/8 (blue) and 9/11 to 14/16 (magenta)






REFERENCE RESULTS

Differential Time Domain

TDR Response

- Based on frequency-to-time domain transformation within Ansoft's HFSS application
- Rise-time of 25ps (20-80%)
- Upper port (blue), Lower port (magenta)
- Into terminals 1/3 (blue) & 9/11 (magenta) on Host Board Side





REFERENCE RESULTS

Differential Time Domain (Continued)

TDT Response

- Based on frequency-to-time domain transformation within Ansoft's HFSS application
- Rise-time of 25ps (20-80%)
- In to terminals 1/3 (blue) & 9/11 (magenta) on Host Board Side
- Out of terminals 2/4 (blue) & 10/12 (magenta) on module Board Side

