

Item	uEZG UI 7.0 LPC2 478	uEZGUI 7.0 LPC1788	UOM	FDI P/N	Description	uEZGUI 7.0 LPC2478	uEZGUI 7.0 LPC1788	Mfg	Mfg Part Number
1	39	37	EACH	C500234	0.1UF, 0402	C1,C2,C3,C4,C5,C6,C7,C8,C9,C10,C11,C12,C14,C16,C17,C18,C19,C25,C26,C27,C28,C29,C30,C32,C33,C34,C35,C37,C41,C44,C47,C48,C49,C68,C71,C72,C75,C76,(C77),C79	C1,C2,C3,C4,C5,C6,C7,C8,C9,C10,C11,C12,C14,C16,C17,C18,C19,C25,C26,C27,C28,C29,C30,C32,C33,C34,C35,C37,(C41),(C44),C47,C48,C49,C68,C71,C72,C75,C76,(C77),C79	CAL CHIP	GMC04X5R104K16NT
2	10	10	EACH	C500252	10UF,6.3V, 0805	C13,C15,C24,C31,C36,C46,C50,C52,C56,C78	C13,C15,C24,C31,C36,C46,C50,C52,C56,C78	PANASONIC	ECJ-2FB0J106M
3	0	2	EACH	C500239	22PF,0402	(C21,C20)	C21,C20	CAL CHIP	GMC04CG220J50NT
4	4	4	EACH	C500040	18PF,0402	C22,C23,C38,C39	C22,C23,C38,C39	MURATA	GRM1555C1H180JZ01D
5	1	1	EACH	C500250	1000PF, 2KV, 1206	C40	C40	AVX	1206GC102KAT1A
6	1	1	EACH	C500283	0.08F, 3.3V, SUPERCAP	C45	C45	SEIKO INST	XH414HG-IV01E
7	3	3	EACH	C500178	10UF,10V, 0805	C51,C62,C61	C51,C62,C61	MURATA	GRM21BR61A106KE19L
8	2	2	EACH	C500282	0.01UF/ 10000PF, 0402	C53,C54	C53,C54	CAL CHIP	GMC04Y5V103Z50NT
9	2	2	EACH	C500270	4.7UF, 50V, 1206	C57,C58	C57,C58	Taiyo Yuden	UMK316BJ475KL-T
10	1	1	EACH	C500276	2.2UF, 25V, 0805	C59	C59	Murata	GRM21BR71E225KA73L
11	1	1	EACH	C500071	1000PF, 25V, 0603	C60	C60	MURATA	GRM1885C1H102JA01D
12	3	3	EACH	C500061	470PF, 50V, 0603	C63,C64,C65	C63,C64,C65	MURATA	GRM1885C1H471JA01D
13	2	2	EACH	C500073	0.1UF, 0603	C70,C66	C70,C66	KEMET	C0603C104K4RACTU
14	1	1	EACH	C500229	0.022UF, 6.3V, 0603	C67	C67	TDK	C1608X8R1H223K
15	1	1	EACH	C500216	22UF,16V, 1210	C69	C69	CAL CHIP	GMC32X7R226M16NT-LF
16	1	1	EACH	C500284	100UF,6.3V, 1206	(C73),C74	(C73),C74	KEMET	C1206C107M9PACTU
17	1	1	EACH	D500001	LED, RED, 1206	D1	D1	FAIRCHILD	QTLP650D2TR
18	1	1	EACH	D500039	LED, GRN, 1206	D2,(D3)	D2,(D3)	AVAGO	HSMG-C150
19	1	1	EACH	D500080	MMSZ5227, 3.6V, SOD-323	D4	D4	Diodes, Inc.	MMSZ5227BS-7-F
20	1	1	EACH	D500098	BAV74, SOT23	D5	D5	NXP	BAV74,215
21	1	1	EACH	D500097	B160-13-F, sma	D6	D6	Diodes, Inc.	B160-13-F
22	1	1	EACH	D500061	PMEG1030EJ , sod-323	D7	D7	NXP	PMEG1030EJ
			EACH						
23	2	2	EACH	F500021	BLM18AG102SN1D, 0603	FB2,FB1	FB2,FB1	MURATA	BLM18AG102SN1D
24	1	1	EACH	F500019	BLM21PG221SN1D, 0805	FB3	FB3	MURATA	BLM21PG221SN1D
25	1	1	EACH	J500030	HEADER 6	J1	J1	JST	SM06B-SHLS-TF
26	1	1	EACH	J500028	MICROSD	J2	J2	3M	2908-05WB-MG
27	1	1	EACH	J500058	CON5X2 SHR SMT	J3	J3	Samtec	STMM-105-02-L-D-SM
28	1	1	EACH	J500048	FPC, CON50, 0.5MM PITCH, SMD	J4	J4	OMRON	XF2M-5015-1A
29	1	1	EACH	J500054	CON20	J5	J5	OMRON	XF2M-2015-1A
30	1	1	EACH	J500055	CON6	J6	J6	MOLEX	501461-0601
31	1	1	EACH	J500056	CON40	J7	J7	HIROSE	FH12-40S-0.5SH(55)
32	1	1	EACH	J500031	CON4, 1MM, FPC, SMT	J8	J8	MOLEX	52271-0469
33	1	1	EACH	LCD0015	LCD, SII, 7.0" WVGA TOUCH 70WVW2TZ0	LCD1	LCD1	Seiko Instruments, Inc.	70WVW2T
34	1	1	EACH	SP00012	SPEAKER	LS1	LS1	Star Micronics	NDT-03C
35	1	1	EACH	L500065	DR74-6R8-R	L1	L1	Coiltronics	DR74-6R8-R
36	2	2	EACH	J500027	CON-USB-MINIB-DX2R005HN2E700	P2,P1	P2,P1	JAE	DX2R005HN2E700
37	1	1	EACH	T500034	MMBT2222A, SOT23	Q1	Q1	ON SEMI	MMBT2222ALT1G
38	1	1	EACH	T500045	PDTA123YT, SOT23	Q2	Q2	NXP	PDTA123YT
39	1	1	EACH	T500055	FDN358P, SOT23	Q3	Q3	FAIRCHILD	FDN358P
40	0	0	EACH	J500059	DF13-2P-1.25H(21), 2POS, 1.25MM, RA, SMT	(J9)	(J9)	HIROSE	DF13-2P-1.25H(20)
41	0	0	EACH	J500057	DF13-3P-1.25H(21), 3POS, 1.25MM, RA, SMT	(J10)	(J10)	HIROSE	DF13-3P-1.25H(20)
42	3	3	EACH	R500436	0R0, 0402	R1,R9,R50,(R2,R30,R31,R49)	(R1,R9),R50,R2,(R30,R31),R49	CAL CHIP	RM04J000CT-LF

