



www.lemo.com

SUMMARY

Wires

Low voltage 5



Image is for illustrative purpose only

Series 1B

Termination type Female print 90° PCB

IP rating 50

AWG wire size 30.00 - 22.00 Cable Ø 0.00 - 0.00 mm

Status active

Matching parts FGA.1B.305.CLAD42

Download

Request a quote
PCB Eagle Pattern
PCB Altium Pattern
PCB KiCad Pattern

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model EC*: Fixed receptacle with two nuts and elbow contacts for printed circuit (back panel

mounting)

Keying 2 keys (alpha=30, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Weight 11.04 g

Performance

Configuration 1B.305 : 5 Low Voltage

Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current

Specifications

Contact Type: Print (elbow)
Contact Dia.: 0.9 mm (0.035in)

R (max): 4.8 mOhm

Vtest (contact-shell): 1150 V (AC), 1630 V (DC) Vtest (contact-contact): 1250 V (AC), 1770 V (DC)

Others

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.


Endurance (Shell): 5000


Temp (min / max): -55°C / +250°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS







Dimensions

	А	В	E	Lmax	М	Nmax	S1	S 3	е
mm.	16	15.8	6	32.96	3.5	20.3	10.5	14	M12x1.0
in.	0,63	0,62	0,24	1,30	0,14	0,80	0,41	0,55	

RECOMMENDED BY LEMO

Tools

Spanner 2: <u>DCH.91.161.PA</u>

Spanner wrench: Socket for torque wrench DCM.1S.M12.4

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

