# Product data sheet Characteristics

# ZB5AW543

Head for illuminated push button, Harmony XB5, XB4, red flush pushbutton Ø22 mm spring return integral LED





Main	
Range of Product	Harmony XB5
Product or Component Type	Head for illuminated push-button
Device short name	ZB5
Product Compatibility	Not compatible with legend holder Integral LED
Bezel material	Dark grey plastic
Mounting diameter	0.87 in (22 mm)
Sale per indivisible quantity	1
Head type	Standard
Shape of signaling unit head	Round
Type of operator	Spring return
Operator profile	Red flush, unmarked
Operator additional information	Clear boot

#### Complementary

Complementary				
CAD overall width	1.18 in (30 mm)			
CAD overall height	1.18 in (30 mm)			
CAD overall depth	1.46 in (37 mm)			
Net Weight	0.04 lb(US) (0.019 kg)			
Resistance to high pressure washer	1015.26 psi (7000000 Pa) 131 °F (55 °C) 0.1 m			
Mechanical durability	1000000 cycles			
Main group	Illum push-button			
Group of product	Flush push integral LED			
Station name	XALD 15 cut-outs XALK 25 cut-outs			
Cap/operator or lens colour	Red			
Marking	Unmarked			
Electrical composition code	M1 6 single front mounting integral LED M2 6 single and double front mounting integral LED M6 2 single front mounting integral LED and transformer M10 2 single front mounting integral LED MF1 2 single front mounting integral LED MR1 2 single rear mounting integral LED			
Device presentation	Basic sub-assemblies			

#### Environment



Standards	EN/IEC 60947-5-1	
	CSA C22.2 No 14	
	EN/IEC 60947-1	
	JIS C8201-5-1	
	GB 14048.5	
	UL 508	
	EN/IEC 60947-5-4	
	JIS C8201-1	
Product Certifications	UL Listed	
	CSA	
	LROS (Lloyds register of shipping)	
	GL	
	DNV	
	BV	
Vibration resistance	5 gn 2500 Hz)IEC 60068-2-6	
Shock resistance	30 gn 18 ms) half sine wave acceleration IEC 60068-2-27	
	50 gn 11 ms) half sine wave acceleration IEC 60068-2-27	

## Ordering and shipping details

22467 - PUSHBUTTONS,22MM(PLASTIC) NEW CS2		
1		
0.71 oz (20 g)		
Yes		
FR		
	CS2 3389110924053 1 0.71 oz (20 g) Yes	

# Packing Units

Unit Type of Package 1	PCE
Package 1 Height	2.13 in (5.4 cm)
Package 1 width	1.34 in (3.4 cm)
Package 1 Length	1.73 in (4.4 cm)
Unit Type of Package 2	S01
Number of Units in Package 2	75
Package 2 Weight	3.80 lb(US) (1.725 kg)
Package 2 Height	5.91 in (15 cm)
Package 2 width	5.91 in (15 cm)
Package 2 Length	15.75 in (40 cm)

# Offer Sustainability

Sustainable offer status	Green Premium product			
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov			
REACh Regulation	REACh Declaration			
REACh free of SVHC	Yes			
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) <sup>Pro-</sup> EU RoHS Declaration			
Mercury free	Yes			
RoHS exemption information	₽ Yes			
China RoHS Regulation	China RoHS Declaration			
Environmental Disclosure	Product Environmental Profile			
Circularity Profile	End Of Life Information			


## Contractual warranty

Warranty

18 months

Product data sheet Dimensions Drawings **ZB5AW543** 


### Dimensions



# ZB5AW543

### Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)

Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board




(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3  $_{0}^{+0.4}$ ) / Ø0.89 in. recommended (Ø0.88 in.  $_{0}^{+0.016}$ )

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

#### **Detail of Lug Recess**




(1) Diameter on finished panel or support

(2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.

(3) Ø22.5 mm recommended (Ø22.3  $_{0}^{+0.4}$ ) / Ø0.89 in. recommended (Ø0.88 in.  $_{0}^{+0.016}$ )

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

#### Panel Cut-outs (Viewed from Installer's Side)




A: 30 mm min. / 1.18 in. min.

B: 40 mm min. / 1.57 in. min.

### Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)


Dimensions in mm



A: 30 mm min.

B: 40 mm min.

Dimensions in in.








#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2 30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
  - $\circ~$  every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (2) Panel
- (2) Nut
- (4) Printed circuit board


#### Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•


Dimensions An + 18.1 relate to the Ø 2.4 mm  $\pm$  0.05 / 0.09 in.  $\pm$  0.002 holes for centring adapter ZBZ01.

# ZB5AW543

### Electrical Composition Corresponding to Codes M1 and M7



## Electrical Composition Corresponding to Codes M2 and M8



#### Electrical Composition Corresponding to Codes M6 and P2



### Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



#### Legend

Single contact

Double contact

Light block

#### Possible location

