


## L4018C220MDWDT

Aliases (L4018C220MDWDT)

Not for New Design • Scheduled EOL - Last date to buy 30 JUN 2023 KEMET, L-DWD, Power, 22 uH, 20%, 4018(1616)



| General Information |   |  |
|---------------------|---|--|
| Series              | L-DWD   |  |
| Style               | SMD   |  |
| Chip Size           | 4018(1616)  |  |
| Description         | Shielded, Surface Mount Inductor  |  |
| Features            | Low Profile   |  |
| RoHS                | Yes   |  |
| Notes               | Last Order Date June 30, 2023. Suggested Replacement -<br>https://productfinder.pulseelectronics.com/part/BWVS00404018220M00. |  |

Click here for the 3D model.

| Dimensions |                |  |
|------------|----------------|--|
| L          | 4mm +/-0.2mm   |  |
| W          | 4mm +/-0.2mm   |  |
| Т          | 1.8mm MAX      |  |
| S          | 2.5mm +/-0.2mm |  |
| LL         | 1.1mm +/-0.2mm |  |

| Packaging Specifications |      |  |  |
|--------------------------|------|--|--|
| Packaging                | T&R  |  |  |
| Packaging Quantity       | 3500 |  |  |

| Specifications          |                 |  |  |  |
|-------------------------|-----------------|--|--|--|
| Inductance              | 22 uH           |  |  |  |
| Inductance Tolerance    | 20%             |  |  |  |
| Temperature Range       | -25/+120°C      |  |  |  |
| Shielded                | Yes             |  |  |  |
| Current                 | 590 mAmps (MAX) |  |  |  |
| DC Resistance           | 0.36 Ohms       |  |  |  |
| Self-Resonant Frequency | 16 MHz          |  |  |  |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.