

T493X336K025CH6130

T493 HRA, Tantalum, MnO2 Tantalum, HRA, 33 uF, 10%, 25 VDC, SMD, MnO2, Molded, High Reliability, C (0.01%/1000 Hrs), 175 mOhms, 7343, Height Max = 4.3mm

CATHODE (-) END VIEW SIDE VIEW W - B Ĥ т /Т X / -S- -- G -- - S-BOTTOM VIEW ANODE (+) END VIEW Termination cutout at KEMET's option, either end - A -Glue pad Ė shape/design at KEMET's option Ê 1 Ρ R

1

В

General Information		
Series	T493 HRA	
Dielectric	MnO2 Tantalum	
Style	SMD Chip	
Description	SMD, MnO2, Molded, High Reliability	
Features	High Reliability	
RoHS	No	
Prop 65	WARNING: Cancer and reproductive harm - http://www.p65warnings.ca.gov.	
SCIP Number	1dd2e1b8-26dd-4d52-927c-6f9d519011aa	
Termination	Solder Coated	
AEC-Q200	No	
Component Weight	654.04 mg	

Click here for the 3D model.	

Dimensions	
Footprint	7343
L	7.3mm +/-0.3mm
W	4.3mm +/-0.3mm
Н	4mm +/-0.3mm
т	0.13mm REF
S	1.3mm +/-0.3mm
F	2.4mm +/-0.1mm
А	3.8mm MIN
В	0.5mm +/-0.15mm
E	3.5mm REF
G	3.5mm REF
Р	1.7mm REF
R	1mm REF
Х	0.1mm +/-0.1mm

Packaging Specifications			
Packaging	T&R, 178mm		
Packaging Quantity	500		

Specifications				
Capacitance	33 uF			
Capacitance Tolerance	10%			
Voltage DC	25 VDC (85C), 16.75 VDC (125C)			
Temperature Range	-55/+125°C			
Rated Temperature	85°C			
Dissipation Factor	6% 120Hz 25C			
Failure Rate	C (0.01%/1000 Hrs)			
Resistance	0.175 Ohms (100kHz 25C)			
Ripple Current	957 mA (rms, 100kHz 25C)			
Leakage Current	8.3 uA (5min 25°C)			
Testing and Reliability	Standard Testing Only			

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.