Product data sheet Characteristics

ZB5AA68

Harmony XB5, Illuminated push button head, plastic, flush, blue, Ø22, spring return, integral LED, for insetion of legend, unmarked





Main

Range of Product	Harmony XB5
Product or Component Type	Head for illuminated push-button
Device short name	ZB5
Product Compatibility	Integral LED
Bezel material	Dark grey plastic
Mounting diameter	0.87 in (22 mm)
Sale per indivisible quantity	1
Head type	Standard
Shape of signaling unit head	Round
Type of operator	Spring return
Operator profile	Blue flush, unmarked
Operator additional information	For insertion of legend

Complementary

Device presentation	Basic element		
	SR2 2 single rear mounting		
	SF2 2 single front mounting		
	C14 2 single front mounting		
	C3 6 single front mounting C4 6 single and double front mounting		
	MR1 2 single rear mounting integral LED		
	MF1 2 single front mounting integral LED		
	M10 2 single front mounting integral LED		
	M6 2 single front mounting integral LED and transformer		
	M2 6 single and double front mounting integral LED		
Electrical composition code	M1 6 single front mounting integral LED		
Marking	Unmarked		
Cap/operator or lens colour	Blue		
	XALK 25 cut-outs		
Station name	XALD 15 cut-outs		
Group of product	Flush push with inser of legend		
Main group	Illum push-button		
Mechanical durability	10000000 cycles		
Resistance to high pressure washer	1015.26 psi (7000000 Pa) 131 °F (55 °C) 0.1 m		
Net Weight	0.04 lb(US) (0.018 kg)		
CAD overall depth	1.18 in (30 mm)		
CAD overall height	1.14 in (29 mm)		
CAD overall width	1.14 in (29 mm)		

Environment

Protective treatment	TC		
Ambient Air Temperature for Storage	-40158 °F (-4070 °C)		
Ambient air temperature for operation	-40158 °F (-4070 °C)		
Overvoltage category	Class II IEC 60536		
IP degree of protection	IP66 IEC 60529 IP67 IP69 IP69K		
NEMA degree of protection	NEMA 13 NEMA 4X		
IK degree of protection	IK03 EN 50102		
Standards	EN/IEC 60947-5-4 EN/IEC 60947-1 JIS C8201-5-1 EN/IEC 60947-5-1 UL 508 GB 14048.5 CSA C22.2 No 14 JIS C8201-1		
Product Certifications	BV CSA GL LROS (Lloyds register of shipping) UL Listed DNV		
Vibration resistance	5 gn 2500 Hz)IEC 60068-2-6		
Shock resistance	30 gn 18 ms) half sine wave acceleration IEC 60068-2-27 50 gn 11 ms) half sine wave acceleration IEC 60068-2-27		

Ordering and shipping details

Category	22467 - PUSHBUTTONS,22MM(PLASTIC) NEW
Discount Schedule	CS2
GTIN	3389110904765
Nbr. of units in pkg.	1
Package weight(Lbs)	0.71 oz (20 g)
Returnability	No
Country of origin	FR

Packing Units

racking onits	
Unit Type of Package 1	PCE
Package 1 Height	3.23 in (8.2 cm)
Package 1 width	2.05 in (5.2 cm)
Package 1 Length	1.26 in (3.2 cm)
Unit Type of Package 2	BB1
Number of Units in Package 2	5
Package 2 Weight	3.53 oz (100 g)
Package 2 Height	2.28 in (5.8 cm)
Package 2 width	10.43 in (26.5 cm)
Package 2 Length	1.34 in (3.4 cm)
Unit Type of Package 3	S03
Number of Units in Package 3	150
Package 3 Weight	7.70 lb(US) (3.492 kg)
Package 3 Height	11.81 in (30 cm)
Package 3 width	11.81 in (30 cm)
Package 3 Length	15.75 in (40 cm)

Offer Sustainability

Sustainable offer status	Green Premium product		
California proposition 65	WARNING: This product can expose you to chemicals including: Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov		
REACh Regulation	☑ REACh Declaration		
REACh free of SVHC	Yes		
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration		
Toxic heavy metal free	Yes		
Mercury free	Yes		
RoHS exemption information	€Yes		
China RoHS Regulation	China RoHS Declaration		
Environmental Disclosure	Product Environmental Profile		
Circularity Profile	End Of Life Information		


Contractual warranty

Warranty 18 months

Product data sheet Dimensions Drawings


ZB5AA68

Dimensions



Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- (1) Diameter on finished panel or support
- (2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- (3) Ø22.5 mm recommended (Ø22.3 $_0$ $^{+0.4}$) / Ø0.89 in. recommended (Ø0.88 in. $_0$ $^{+0.016}$)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18


Detail of Lug Recess



- (1) Diameter on finished panel or support
- (2) For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended.
- (3) Ø22.5 mm recommended (Ø22.3 $_0$ $^{+0.4})$ / Ø0.89 in. recommended (Ø0.88 in. $_0$ $^{+0.016})$

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

Panel Cut-outs (Viewed from Installer's Side)




A: 30 mm min. / 1.18 in. min.

B: 40 mm min. / 1.57 in. min.

Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)


Dimensions in mm



A: 30 mm min.

B: 40 mm min.

Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.


General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
 - $\circ~$ every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
 - o with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.




- (1) Head ZB5AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- 2 1 hole Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 for centring adapter ZBZ01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm \pm 0.05 / 0.09 in. \pm 0.002 holes for centring adapter ZBZ01•.

Electrical Composition Corresponding to Code C3
Electrical Composition Corresponding to Code C4
Electrical Composition Corresponding to Codes C14, SF2 and SR2
Electrical Composition Corresponding to Codes M1 and M7
Electrical Composition Corresponding to Codes M2 and M8



Electrical Composition Corresponding to Codes M6 and P2



Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



Electrical Composition Corresponding to Codes C14, SF2 and SR2

Legend

Single contact

Double contact

Light block

Possible location

Life Is On Schneider