



Item description

The WAGO USB Communication Cable connects a PC (notebook) to both the service interface of the 857 Series Signal Conditioners and the configuration interface of WAGO's I/O fieldbus couplers/controllers.

Notice!

Using the WAGO 759-923 USB Communication Cable
in combination with select programmable fieldbus controllers
requires the specific firmware versions listed below:

750-841: Firmware Version 12 (or higher)

750-872/0020-0000: Firmware Version 2 (or higher)

Data

Technical data

Connection type	4-pole male connector - USB A-type plug
Pole number	4
Cable length	5 m
Supported operating systems	Windows XP (SP3 or higher) Windows 7

Subject to changes. Please also observe the further product documentation!



Windows 10
Windows 11

Physical data

Width	15 mm / 0.591 inches
Height	50 mm / 1.97 inches
Depth	19 mm / 0.748 inches

Mechanical Data

Weight	114.3 g
--------	---------

Environmental requirements

Ambient temperature (operation)	-25 ... +70 °C
Protection type	IP20
EMC immunity to interference	per EN 61000-4-3, EN 61000-4-6
EMC emission of interference	per EN 55022
Fire load	0.132 MJ

Commercial data

Product Group	15 (I/O System)
eCl@ss 10.0	27-24-22-20
eCl@ss 9.0	27-24-22-20
ETIM 8.0	EC000237
ETIM 7.0	EC000237
PU (SPU)	1 pcs
Packaging type	bag
Country of origin	DE
GTIN	4045454765200
Customs tariff number	85444290900

Environmental Product Compliance

RoHS Compliance Status	Compliant, No Exemption
------------------------	-------------------------

Downloads**Documentation****Manual**

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



System Manual WAGO I/O System 750/753 Decentralized Automation Technology	V 3.3.0 2023 May 4	pdf 8.8 MB	Download
Bid Text			
750-923/000-001 docx - Datei	2019 Jun 26	docx 15.0 kB	Download
750-923/000-001 X81 - Datei	2019 Feb 19	xml 4.1 kB	Download
Tutorial			
Set IP address with Ethernet Settings In this video we are demonstrating how you can set a IP address with Ethernet Settings. Content: 00:27 – Chapter #1 Download and install software; 00:56 – Chapter #2 Open Ethernet Settings; 01:10 – Chapter #3 Establish serial Connection; 01:34 – Chapter #4 Set IP address; 02:10 – Chapter #5 Check IP address	3.0 2017 Dec 18	mp4 88.3 MB	Download
System Description			
750/753 Series I/O-System – General Product Information		pdf 1.7 MB	Download
CAD/CAE-Data			
CAE data			
EPLAN Data Portal 750-923/000-001		URL	Download
WSCAD Universe 750-923/000-001		URL	Download
WSCAD Universe 750-923/000-001		URL	Download
EPLAN Data Portal 750-923/000-001		URL	Download
Device Files			
Device Driver			
WAGO USB Service Kabel Treiber / Serie 750 und 857	6.5.3.0 2014 Sep 10	zip 4.8 MB	Download

Subject to changes. Please also observe the further product documentation!



Environmental Product Compliance

Compliance Search

Environmental Product Compliance 750-923/000-001

URL

Download

Configuration cable; USB connector; Length: 5 m

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.