



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE2647 (PNP) & NTE2648 (NPN) Silicon Complementary Transistors General Purpose Amp TO-220 Full Pack Type Package

**Features:**

- High Transition Frequency

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Collector-Base Voltage, $V_{CBO}$ .....	230V
Collector-Emitter Voltage, $V_{CEO}$ .....	230V
Emitter-Base Voltage, $V_{EBO}$ .....	5V
Collector Current, $I_C$ .....	1A
Collector Power Dissipation, $P_C$	
$T_A = +25^\circ\text{C}$ .....	2.0W
$T_C = +25^\circ\text{C}$ .....	20W
Operating Junction Temperature, $T_J$ .....	+150°C
Storage Temperature Range, $T_{stg}$ .....	-55° to +150°C

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Collector Cutoff Current	$I_{CBO}$	$V_{CB} = 230V, I_E = 0$	-	-	1.0	$\mu\text{A}$
Emitter Cutoff Current	$I_{EBO}$	$V_{EB} = V, I_C = 0$	-	-	1.0	$\mu\text{A}$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = 10\text{mA}, I_B = 0$	230	-	-	V
DC Current Gain	$h_{FE}$	$V_{CE} = 5V, I_C = 100\text{mA}$	100	-	320	
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = 500\text{mA}, I_B = 50\text{mA}$	-	-	1.5	V
Base-Emitter Voltage	$V_{BE}$	$V_{CE} = 5V, I_C = 500\text{mA}$	-	-	1.0	V
Transition Frequency NTE2747	$f_T$	$V_{CE} = 10V, I_C = 100\text{mA}$	-	70	-	MHz
NTE2748			-	100	-	MHz
Collector Output Capacitance NTE2647	$C_{ob}$	$V_{CB} = 10V, I_E = 0, f = 1\text{MHz}$	-	30	-	pF
NTE2748			-	20	-	pF

