

# PHJ.3B.303.CLAD12

## SUMMARY

#### # Wires

Low voltage



Image is for illustrative purpose only

Series	3B	
Termination type	Male solder	
IP rating	50	
AWG wire size	22.00 - 14.00	
Cable Ø	10.80 - 11.90 mm	
Status	active	
Matching parts	FHJ.3B.303.CLLD12	

3

### Request a quote

Download

Catalog

## **TECHNICAL DETAILS**

#### **Mechanics**

Shell Style/Model	PH*: Free receptacle, cable collet
Keying	2 keys (alpha=37.5, plug: female contacts, receptacle: male contacts)
Housing Material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces

#### Performance

Configuration	3B.303: 3 Low Voltage	
Insulator	L: PEEK (UL 94 / V-0/1.5)	
Rated Current	25 Amps	


#### **Specifications**


Contact Type: Solder Contact Dia.: 2 mm (0.079in) Bucket Dia.: 1.8 mm (0.071in) Max. Solid Conductor: 1.5 mm^2 (AWG 14) Max. Stranded Conductor: 1.5 mm^2 (AWG 16) R (max): 3.3 mOhm Vtest (contact-shell): 1500 V (AC), 2120 V (DC) Vtest (contact-contact): 1900 V (AC), 2700 V (DC)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Others Endurance (Shell): 5000 Temp (min / max): -55°C / +250°C Humidity (max): <=95% [at 60 deg C /140 F] Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [ 6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

### DRAWINGS







#### Dimensions

	А	L	S1	S2
mm.	19	56	15	14
in.	0,75	2,20	0,59	0,55

### **RECOMMENDED BY LEMO**

#### Tools

Spanner wrench:

DCD.3B.ZZZ.PA140

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.