

# POWER TRANSFORMER Chassis Mount: International Series

## **VPL20-2500**

## Electrical Specifications (@25C)

- 1. Maximum Power: 50.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
- 3. Output Voltage Series: 20.0V CT@ 2.50A, Parallel: 10.0V @ 5.0A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.

### Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

## **Agency Files:**


TUV Certificate No.: R72103639, EN60950, Information Technology



Dimens	sions:	Units: In inches				

Α	В	С	D	Е	F
2.562	4.00	2.250	3.562	8.00	0.187

Weight: 2.3 lbs.



## Connections<sup>1</sup>:

Input: Series – BLK to BLU, Jumper WHT to BRN


Parallel - BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series - RED to GRY, Jumper YEL to VIO

Parallel - RED to GRY, Jumper RED to VIO and YEL to GRY

**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.



**SCHEMATIC** 

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571

Publish Date: June 3, 2019

<sup>&</sup>lt;sup>1</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.