



1559-1610, 2400-2500, 5150-5875 & 5925-7125 MHz GNSS / Wi-Fi 6E BAND CABLED ANTENNA

Part Numbers: 2108937-1, 2108937-2

2108937-3, 2108937-4


FEATURES & BENEFITS


- GNSS, also including Wi-Fi 6E new 6GHz band, Bluetooth, ZigBee
- Adhesive backing on the FPC simplifies mounting within the device
- Ground-plane independent design
- Different cable length and connector options available


SPECIFICATIONS

Frequency Range (MHz)	1559 - 1610	2400 - 2500	5150 - 5875	5925 - 7125		
VSWR	< 1.7:1	< 1.6:1	< 1.8:1	< 1.4:1		
Average Efficiency	61 %	59 %	49 %	48 %		
Peak Gain	1.2 dBi	0.4 dBi	0.6 dBi	4.2 dBi		
Average Gain	-2.2 dBi	-2.3 dBi	-3.1 dBi	-3.3 dBi		
Power Handling	10 Watt cw					
Feed Point Impedance	50 ohms unbalanced					
Polarization	Linear					
Size	50.0 mm x 15.0 mm x 0.15mm					
Weight	< 1.05 g					
Mounting	Adhesive Tape					
Mating Connector	MHF-type receptacle (TE PN 2337019-1)					
Cable	Coaxial Cable : 1.13mm Dia.					
Operating Temperature	-40 to +85°C					
Storage Temperature	-40 to +85°C					
Hazardous Materials	A certificate of conformance is available from the product page on TE website					












RF DATA







RADIATION PATTERN



RADIATION PATTERN



KEEP OUT AREA




NOTES: 1. Antenna designed to be mounted on plastic cover.

2. Area in Blue above indicates Keep Out Area.

3. For more information please call TE.

Dimensions: mm Diagram is not to scale


DIMENSIONS



MATING COMPONENTS

2108937-1 2108937-2	50.0 100.0	1.968 3.937	MHE-TYPE DILIG	RECEPTACLE (TE PN: 2337019-1)	
2108937-3	150.0	5.905	WITH TIPE FEOG	RECEPTACLE (TE FIN. 2557015-1)	
2108937-4	200.0	7.784			
PART	MM	INCH	CONNECTOR TYPE	PART NUMBER	IMAGE
NUMBER	CABLE LI	ENGTH(A)	(ON CABLE)	MATING COMPONENTS	

PACKAGING



TE TECHNICAL SUPPORT CENTER

USA: +1 (800) 522-6752 Canada: +1 (905) 475-6222 Mexico: +52 (0) 55-1106-0800 Latin/S. America: +54 (0) 11-4733-2200 +49 (0) 6251-133-1999 Germany: UK: +44 (0) 800-267666 France: +33 (0) 1-3420-8686 +31 (0) 73-6246-999 Netherlands: China: +86 (0) 400-820-6015

For phone numbers in other countries, go to te.com/support-center

te.com

TE Connectivity, TE Connectivity (logo) are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

© 2021 TE Connectivity Ltd. family of companies All Rights Reserved.

10/2021

