

## USB RS-232 Serial Adapter w/ LED Indicator

Model Number: FTDI-LED

Rev 03.210315



This USB 2.0 RS-232 Serial Adapter is the easiest way to add a serial port to your computer. Newer computers today are unequipped to support peripherals requiring a serial RS-232 connection because they lack serial ports; this affects PDA, digital camera, and GPS type equipment that may be used on your system.

### Features

- 5ft standard USB to rs-232 cable with double color led display of full signal power
- Full rs-232 signal led tester output via dual color display
- Ftdi chip USB to rs-232 cable with led monitor
- Easy test rs-232 host to device link
- Os compatibility: Windows 7, 8 and Windows 10 as well as Linux and MacOS 10.X

### Product Information

- Model Number: FTDI-LED
- Packing List:
  -

## Specifications

### OVERVIEW

Product Type	Serial Adapter
Electrical Protections	15KV ESD Protection
Mountable	
Material	
Compliance	N/A
LED indicators	All Signals
Requires Host to Function	

### 0

Serial Modes	RS232
RS232 Signals	DCD, RxD, TxD, DTR, GND, DSR, RTS, CTS, RI
RS422 Signals	
RS485 2-wire Signals	
RS485 4-wire Signals	

### SERIAL SPECS

Maximum Data Rate	460.8 Kbps
Minimum Data Rate	300 baud/bps
Data Bits	
Parity	
Stop Bits	
Flow Control	
FIFO	

**Specifications Cont.****ENVIRONMENTAL**

Operating Temperature	-40C ~ 85C
Operating Humidity	5% to 95% RH
Storage Temperature	-40C ~ 85C

**PHYSICAL**

Length	inches
Width	inches
Height	inches
Item Weight	lbs
Ship Weight	0.1870 lbs

**OS SUPPORT**

Supported Operating Systems	Linux, OSX 10, Windows 10, Windows 8, Windows 7
-----------------------------	---

**WARRANTY**

Warranty Period	ONE YEAR
-----------------	----------

**PRODUCT URL**

FTDI-LED Product Page	
-----------------------	--