

# POWER TRANSFORMER PC MOUNT: WORLD SERIES

# **VPP28–1060**

## Electrical Specifications (@25C)

- 1. Maximum Power: 30.0VA
- 2. Input: Series: 230VAC, 50/60Hz; Parallel: 115VAC, 50/60Hz
- 3. Output: Series<sup>1</sup>: 28.0V CT@ 1.06A; Parallel<sup>2</sup>: 14.0V @ 2.12A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance: 100MΩ
- 7. Hipot: 4000VAC between primary to secondary and windings to core.
- 8. Recommended Fuse3:

Series: Littelfuse p/n 313 1.25HXP, 1.25A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-1¼, 1.25A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-2½, 2.5A 250V, ¼ x 1 ¼

#### **Construction:**

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safety:

Since the dual bobbin construction effectively reduces capacitance, electrostatic shielding is not required. World Series Transformers are designed and manufactured to meet the following agency approvals:

Units: In inches



#### Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. UL: File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3. CSA: File LR 221330. C22.2 NO. 66, General Purpose. TUV: File R72103639, EN 60950, (IEC950) information Technology Equipment.

	<b>_</b>	
Α.	Dimensions:	

н	W	D	А	В	С	ML	MD	MW
1.562	2.625	2.187	0.550	0.275	1.680	-	1.75	2.187

B. PIN DIM. : 0.045 SQ

C. WT Lbs. : 1.15

D. Mounting Holes: 0.156 dia. x 4

### Connections<sup>4</sup>:

Input: Series – Pin 1 to Pin 6, Jumper Pin 4 to Pin 3

Parallel – Pin 1 to Pin 6, Jumper Pin 1 to Pin 4 and Pin 3 to Pin 6 **Output:** Series – Pin 7 to Pin 12, Jumper Pin 9 to Pin 10 Parallel – Pin 7 to Pin 12, Jumper Pin 7 to Pin 10 and Pin 9 to Pin 12

**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements

of 2015/863/EU, known as the RoHS 3 initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


<sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


<sup>4</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757


460 Harley Knox Blvd. Perris, California 92571














Publish Date: June 3, 2019

<sup>&</sup>lt;sup>1</sup> Non-Inherently limited. Class 3.

<sup>&</sup>lt;sup>2</sup> Non-Inherently limited. Class 2 not wet, Class 3 wet.