


TOLERANCE UNLESS OTHERWISE SPECIFIED	
.X	±0.25
.XX	±0.13

.XXX ±0.05

THIS IS A C.A.D. GENERATED DRAWING DO NOT MAKE MANUAL REVISIONS TO MASTER.



ISSUE NUMBER ORIGINAL



NOTES:

MATERIAL:

HOUSING: THERMOPLASTIC POLYESTER, UL94V-0

SHELL: STEEL, TIN PLATED

CONTACT: COPPER ALLOY, GOLD FLASH PLATED

OPERATING TEMPERATURE: -55°C ~ 125°C

10A (CURRENT) POWER/CO-AX CONTACT RATING:

(IF PRESENT)


SIGNAL CONTACT CURRENT RATING: 5A PER CONTACT

SIGNAL CONTACT RESISTANCE: $10m\Omega$ MAX.

INSULATOR RESISTANCE: 5000MΩ min.

DIELECTRIC

WITHSTANDING VOLTAGE: 1000V AC rms



COMBINATION D-SUB



EDAC INC TORONTO, ONTARIO CANADA

THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF EDAC INC..AND SHALL NOT BE REPRODUCED, OR COPIED OR USED AS THE BASIS FOR THE MANUFACTURE OR SALE OF APPARATUS WITHOUT WRITTEN PERMISSION.

	SW REFERENCE NO.: 629 COMBO ASSEMBLY		
	DRAWN: C.B	DATE: JAN. 01/2019	
	CHECKED:	DATE:	
	SCALE: (IN C.A.D. 1:1)	SHEET 1 OF 2	
ĺ	DRAWING NUMBER: 629-47W1250-1T6		

PART NUMBER: 629-47W1250-1T6

THIS SERIES FULLY CONFORMS TO THE EUROPEAN UNION DIRECTIVES 2011/65/EU FOR RoHS COMPLIANCY.

TOLERANCE UNLESS OTHERWISE SPECIFIED

.X ±0.25 .XX ±0.13 .XXX ±0.05

THIS IS A C.A.D. GENERATED DRAWING DO NOT MAKE MANUAL REVISIONS TO MASTER.



ISSUE NUMBER (1) ORIGINAL

00 2W2

2WK2

o€:

5W1

00000 3W3

000 3WK3

0...0 7W2

...o...

11W1

00000 5W5

9W4

0000

13W3

0:::::::0

..... 21W1

17W2

000000::: 13W6

(00:::::000 lo

17W5

00000000 8W8

000:::::0 25W3

O :::::::::::: 27W2

0000000

21W4

00000000 24W7

36W4





47W1

COMBINATION D-SUB

YOUR CONNECTION TO QUALITY & SERVICE

EDAC INC TORONTO, ONTARIO CANADA

THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF EDAC INC..AND SHALL NOT BE REPRODUCED,OR COPIED OR USED AS THE BASIS FOR THE MANUFACTURE OR SALE OF APPARATUS WITHOUT WRITTEN PERMISSION.

629 COMBO ASSEMBLY SW REFERENCE NO.: DRAWN: DATE: JAN. 01/2019 CHECKED: DATE: SHEET 2 OF 2 SCALE: N.T.S 629-47W1250-1T6 ISSUE DRAWING NUMBER:

629-47W1250-1T6

PART NUMBER:

COMPLIANT