

### BeStar Technologies Inc.

Address: 761 N. 17th Street Unit 4, St. Charles, IL 60174
Tel: 847-261-2850 E-mail: sales@bestartech.com Web: www.bestartech.com

Document Number: 0404-17

Revision : A4 **Total Pages** : 5

Prepare by : Loki, Lo

: 4 January, 2013 Date

# **SENER** Brand Power Product

www.jlsener.com

**Document Type** : Specification

**Product Type** : Lithium Manganese Dioxide (LiMnO2) Cylindrical Battery

**Ordering Code** : SCR1/3N Cell Part Number : CR1/3N

A1 - New issue created by Leo, sin on 20 Jul., 2004	
A2 - Updated format & layout by Holmes, Poon on 24 Apr., 2012	
A3 - Updated section 4 by Holmes, Poon on 7 May, 2012	
A4 - Updated section 4 ~ 7 by Loki, Lo on 4 Jan., 2013	

This material is the property of BeStar Technologies Inc. Unauthorized copying or use of this material is prohibited.

# 1. Purpose and Scope

This document contains both general requirements, qualification requirements, and those specific electrical, mechanical requirements for this part.

# 2. Description

Ø11.7 x 10.9 mm Lithium Manganese Dioxide (LiMnO2) cylindrical battery, RoHS compliant.

## 3. Application

Computers and Peripherals, Portable Equipment, DECT phone, etc.

# 4. Component Requirement

### 4.1 General Requirement

**4.1.1.** Cell Size : Ø11.7 x 10.9 mm

**4.1.2.** Weight : Approx. 3g

**4.1.3.** Operating Temperature : -40°C to +60°C

**4.1.4.** Storage Temperature : -40°C to +60°C

# 4.2 Electrical Requirement

**4.2.1.** Nominal Voltage : 3V

**4.2.2.** Nominal Capacity : 170mAh

**4.2.3.** Standard Discharge Current : 3mA

**4.2.4.** Maximum Continuous Discharge Current : 60mA

**4.2.5.** Maximum Pulse Discharge Current : 140mA

#### 4.3 Standard Characteristics

### **4.3.1.** Temperature Characteristics (Load: 3mA)




Figure 1. Temperature Characteristics (Load: 3mA)

# **4.3.2.** Temperature Characteristics (Load: $1K\Omega$ )




Figure 2. Temperature Characteristics (Load:  $1K\Omega$ )

# **4.3.3.** Discharge Characteristics at Various Currents




Figure 3. Dischage Characteristics at Various Currents

### 5. Test and Measurement

- **5.1. Outer Dimensions**: Samples are measured by caliper with tolerance <0.25%.
- **5.2. Weight**: Samples are measured by balance with sensitivity > 100mg.
- **5.3. Appearance**: No deformation or tarnish should be found by visual inspection.
- **5.4. Open Circuit Voltage** : Samples are measured by voltmeter with internal impedance  $>1M\Omega$  and tolerance <0.25%.
- **5.5. Operating Duration**: Operating duration is counted from nominal voltage to specific cut-off voltage by standard discharge current.
- **5.6. Battery Impedance**: Apply 1KHz, 0.1mA sine wave to samples and measure it's impedance value.
- **5.7. Vibration Resistance**: Secure samples. Vibrated 1000rpm with 2mm peak amplitude in 3 directions (x, y and z). The test duration is 30 minutes per plane.
- **5.8. Leakage Resistance**: Perform heat cycle test according to MIL-STD-202E-106D standard. No leakage should be found after 10 cycles test.

#### 6. Caution

- **6.1.** A battery shall not be stored at temperatures in excess of 45°C. Storage at less than 30°C is recommended. Storage at less than -40°C can deform the plastic parts and may cause a leakage. To prevent self-discharge caused by corrosion, or decrease of insulation, humidity during storage shall be less than 70%.
- **6.2.** The battery has an explosion resistant construction. But the following cautions should be taken because combustible materials such as lithium metal and organic electrolyte are contained in the battery.
  - \* Do not short circuit.
  - \* Do not dispose in fire.
  - \* Do not charge.
  - \* Do not disassemble.
- **6.3.** Keep away from heat source or flame.
- **6.4.** The battery should not be washed by ultrasonic wave washer.
- **6.5.** Do not mix fresh batteries with used or different battery types.

# 7. Mechanical Layout

Unit: mm

Tolerance : Linear  $XX.X = \pm 0.3$ 

 $XX.XX = \pm 0.05$ 

Angular =  $\pm 0.25^{\circ}$ 

(unless otherwise specified)




Figure 4. SCR1/3N Mechanical Layout