

POWER TRANSFORMER Chassis Mount : International Series

VPL25-1000

Electrical Specifications (@25C)

- 1. Maximum Power: 25.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
- 3. Output Voltage Series1: 25.2V CT@ 0.99A, Parallel2: 12.6V @ 1.98A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.
- 6. Recommended Fuse³:

Series: Littelfuse p/n 313 1.25HXP, 1.25A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-1 ¼, 1.25A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-2 ½, 2.5A 250V, ¼ x 1 ¼

Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

Agency Files:

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV Certificate No.: R72103639, EN60950, Information Technology



Dimensions:			Units: In inches		
А	В	С	D	Е	F
1.937	3.250	2.125	2.812	8.00	0.187
Weight: 1.2 lba					

Weight: 1.3 lbs.

Connections⁴:

- Input: Series BLK to BLU, Jumper WHT to BRN Parallel – BLK to BLU, Jumper BLK to BRN and WHT to BLU
- Output: Series RED to GRY, Jumper YEL to VIO Parallel – RED to GRY, Jumper RED to VIO and YEL to GRY

RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


- ² Non-Inherently limited. Class 2 not wet, Class 3 wet.
- ³ Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


⁴ Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571









SCHEMATIC

Publish Date: June 3, 2019

¹ Non-Inherently limited. Class 3.