

www.lemo.com

EHG.2B.804.KLL3

SUMMARY

Wires

Low voltage 4 Coax 1

Series 2B

Termination type Female solder mixed / multi

IP rating 50

AWG wire size 30.00 - 22.00 Cable Ø 1.40 - 9.90 mm

Status active



Image is for illustrative purpose only

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model EH*: Fixed receptacle, nut fixing and protruding shell

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (black chrome) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch

sleeve and mid pieces

Weight 19.36 g

Performance

Configuration 2B.804: 1 Coax (50 Ohm), 4 Low V.

Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 7 Amps

Specifications

Contact Type: Coaxial 50 Ohm (Solder) Type A1

Contact Dia.: 0.7 mm (0.03in)

Max. Solid Conductor: 0.5 mm² (AWG 20) Max. Stranded Conductor: 0.14 mm² (AWG 26)

R (max): 3.8 mOhm

Test voltage (kV rms): 0.75 Test voltage (kV dc): 1.05

Cable type: RG 179 B/U, RG 187 A/U

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Others


Endurance (Shell): 5000


Temp (min / max): -55°C / +250°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS







Dimensions

	A	В	E	L	М	N	S1	\$3	e
mm.	18	19.5	5.1	22.7	12.5	24.6	13.5	17	M15x1.0
in.	0,71	0,77	0,20	0,89	0,49	0,97	0,53	0,67	

RECOMMENDED BY LEMO

Tools

Die Tool: DCP.99.050.TC

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Cables	