AOD780A70/AOI780A70

700V, αMOS5™ N-Channel Power Transistor

General Description

- Proprietary αMOS5™ technology
- Low $R_{DS(ON)}$
- Optimized switching parameters for better EMI performance
- Enhanced body diode for robustness and fast reverse recovery

Applications

- PFC and PWM stages (Flyback, LLC) of Adapter, PC Silverbox,Server,Gaming Power Supply, Industrial, TV,Lighting

Product Summary

V_{DS} @ $T_{j,max}$	800V
I_{DM}	28A
$R_{DS(ON),max}$	< 0.78Ω
$Q_{g,typ}$	11.5nC
E_{oss} @ 400V	1.4μJ

100% UIS Tested
100% R_g Tested

Green Product







Orderable Part Number	Package Type	Form	Minimum Order Quantity
AOD780A70	TO252	Tape & Reel	2500
AOI780A70	TO251A	Tube	3500

Absolute Maximum Ratings T_A=25°C unless otherwise noted

Parameter		Symbol	Maximum	Units
Drain-Source Voltage		V_{DS}	700	V
Gate-Source Voltage		V_{GS}	±20	V
Gate-Source Voltage (dynamic) AC(f>1Hz)		V_{GS}	±30	V
Continuous Drain Current	T_C=25°C	I_D	7.0	A
	T_C=100°C		4.5	
Pulsed Drain Current [C]		I_{DM}	28	
Avalanche Current [C] L=1mH		I_{AR}	1.7	A
Repetitive avalanche energy [C]		E_{AR}	1.5	mJ
Single pulsed avalanche energy [H]		E_{AS}	11	mJ
MOSFET dv/dt ruggedness		dv/dt	100	V/ns
Peak diode recovery dv/dt			20	
Power Dissipation [B]	T_C=25°C	P_D	83	W
	Derate above 25°C		0.7	W/°C
Junction and Storage Temperature Range		T_J, T_{STG}	-55 to 150	°C
Maximum lead temperature for soldering purpose, 1/8" from case for 5 seconds		T_L	300	°C

Thermal Characteristics

Parameter	Symbol	Typical	Maximum	Units
Maximum Junction-to-Ambient [A,D]	$R_{\theta JA}$	45	55	°C/W
Maximum Case-to-sink [A]	$R_{\theta CS}$	-	0.5	°C/W
Maximum Junction-to-Case [D,F]	$R_{\theta JC}$	1.2	1.5	°C/W

Electrical Characteristics (T_J=25°C unless otherwise noted)

Symbol	Parameter	Conditions	Min	Typ	Max	Units
STATIC PARAMETERS						
BV_{DSS}	Drain-Source Breakdown Voltage	I_D=250µA, V_{GS}=0V, T_J=25°C	700			V
		I_D=250µA, V_{GS}=0V, T_J=150°C		800		
BV_{DSS} /ΔTJ	Breakdown Voltage Temperature Coefficient	I_D=250µA, V_{GS}=0V		0.56		V/°C
I_{DSS}	Zero Gate Voltage Drain Current	V_{DS}=700V, V_{GS}=0V			1	µA
		V_{DS}=560V, T_J=125°C			10	
I_{GSS}	Gate-Body leakage current	V_{DS}=0V, V_{GS}=±20V			±100	nA
$V_{GS(th)}$	Gate Threshold Voltage	V_{DS}=5V, I_D=250µA	2.9	3.5	4.1	V
$R_{DS(ON)}$	Static Drain-Source On-Resistance	V_{GS}=10V, I_D=1.4A		0.7	0.78	Ω
g_{FS}	Forward Transconductance	V_{DS}=10V, I_D=1.4A		3		S
V_{SD}	Diode Forward Voltage	I_S=1.4A,V_{GS}=0V		0.8	1.2	V
I_S	Maximum Body-Diode Continuous Current				7	A
I_{SM}	Maximum Body-Diode Pulsed Current [C]				28	A
DYNAMIC PARAMETERS						
C_{iss}	Input Capacitance	V_{GS}=0V, V_{DS}=100V, f=1MHz		675		pF
C_{oss}	Output Capacitance			18		pF
$C_{o(er)}$	Effective output capacitance, energy related [I]	V_{GS}=0V, V_{DS}=0 to 480V, f=1MHz		16.5		pF
$C_{o(tr)}$	Effective output capacitance, time related [J]			72		pF
C_{rss}	Reverse Transfer Capacitance	V_{GS}=0V, V_{DS}=100V, f=1MHz		1.8		pF
R_g	Gate resistance	f=1MHz		3.1		Ω
SWITCHING PARAMETERS						
Q_g	Total Gate Charge	V_{GS}=10V, V_{DS}=480V, I_D=3.5A		11.5		nC
Q_{gs}	Gate Source Charge			4.8		nC
Q_{gd}	Gate Drain Charge			2.8		nC
$T_{d(on)}$	Turn-On DelayTime	V_{GS}=10V, V_{DS}=400V, I_D=3.5A, R_G=5Ω		18		ns
T_r	Turn-On Rise Time			9		ns
$T_{d(off)}$	Turn-Off DelayTime			30		ns
T_f	Turn-Off Fall Time			12		ns
T_{rr}	Body Diode Reverse Recovery Time	I_F=3.5A, dI/dt=100A/µs, V_{DS}=400V		230		ns
I_{rm}	Peak Reverse Recovery Current			16.5		A
Q_{rr}	Body Diode Reverse Recovery Charge			2.5		µC

A. The value of $R_{\theta JA}$ is measured with the device in a still air environment with T_A=25° C.
B. The power dissipation P_D is based on $T_{J(MAX)}$=150° C in a TO252 package, using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used.
C. Repetitive rating, pulse width limited by junction temperature $T_{J(MAX)}$=150° C.
D. The $R_{\theta JA}$ is the sum of the thermal impedance from junction to case $R_{\theta JC}$ and case to ambient.
E. The static characteristics in Figures 1 to 6 are obtained using <300µs pulses, duty cycle 0.5% max.
F. These curves are based on the junction-to-case thermal impedance which is measured with the device mounted to a large heatsink, assuming a maximum junction temperature of $T_{J(MAX)}$=150° C.
G.These tests are performed with the device mounted on 1 in^2 FR-4 board with 2oz. Copper, in a still air environment with T_A=25° C.
H. L=60mH, I_{AS}=0.6A, R_G=25Ω, Starting T_J=25° C.
I. $C_{o(er)}$ is a fixed capacitance that gives the same stored energy as C_{oss} while V_{DS} is rising from 0 to 80% $V_{(BR)DSS}$.
J. $C_{o(tr)}$ is a fixed capacitance that gives the same charging time as C_{oss} while V_{DS} is rising from 0 to 80% $V_{(BR)DSS}$.

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 1: On-Region Characteristics



Figure 2: Transfer Characteristics



Figure 3: On-Resistance vs. Drain Current and Gate Voltage



Figure 4: On-Resistance vs. Junction Temperature



Figure 5: Break Down vs. Junction Temparature



Figure 6: Body-Diode Characteristics

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 7: Gate-Charge Characteristics



Figure 8: Capacitance Characteristics



Figure 9: Coss stored Energy



Figure 10: Maximum Forward Biased Safe Operating Area (Note F)



Figure 11: Power De-rating (Note B)



Figure 12: Current De-rating (Note F)

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 13: Single Pulse Power Rating Junction-to-Case (Note F)



Figure 14: Single Pulse Power Rating Junction-to-Ambient (Note G)



Figure 15: Normalized Maximum Transient Thermal Impedance (Note F)



Figure 16: Normalized Maximum Transient Thermal Impedance (Note G)

Gate Charge Test Circuit & Waveform



Resistive Switching Test Circuit & Waveforms



Unclamped Inductive Switching (UIS) Test Circuit & Waveforms



Diode Recovery Test Circuit & Waveforms