



160.175 MHz Crystal Filter

P/N: AM160.175CR268

| | |
|--|---------------|
| Center Frequency: | 160.175 MHz |
| 1db Bandwidth: | 30Khz +/-5Khz |
| Attenuation in passband of other center frequencies: | 30db min |
| Crystal Spurious: | 30db min |
| Max Input Power: | 8db max |
| Source & Load Impedance: | 50 ohms |
| Insertion loss: | 6db max |

