

AEC-Q200 This component was always RoHS compliant from the first date of manufacture.

RO3156E/E-1/E-2

868.950 MHz SAW Resonator



- Designed for European 868.95 MHz SRD Transmitters
- Very Low Series Resistance
- · Quartz Stability
- Complies with Directive 2002/95/EC (RoHS)
- Tape and Reel Standard per ANSI/EIA-481

The RO3156E is a true one-port, surface-acoustic-wave (SAW) resonator in a surface-mount ceramic case. It provides reliable, fundamental-mode, quartz frequency stabilization of fixed-frequency transmitters operating at 868.95 MHz.This SAW is designed specifically for SRD remote control and wireless security transmitters operating under ETSI EN 300 220.

Absolute Maximum Ratings

Rating	Value	Units
Input Power Level	0	dBm
DC Voltage	12	VDC
Storage Temperature	-40 to +125	°C
Operating Temperature Range	-40 to +125	°C
Soldering Temperature, 10 seconds / 5 cycles maximum	+260	°C

Electrical Characteristics

Characteristic		Sym	Notes	Minimum	Typical	Maximum	Units
Frequency, +25 °C	RO3156E			868.750		869.150	
	RO3156E-1	f_C		868.800		869.100	MHz
	RO3156E-2			868.850		869.050	
Tolerance from 868.95 MHz	RO3156E					±200	
	RO3156E-1	Δf_{C}				±150	kHz
	RO3156E-2					±100	
Insertion Loss		IL			1.2	2.0	dB
Quality Factor	Unloaded Q	Q _U			6700		
	50 $Ω$ Loaded Q	Q_L			800		
Temperature Stability	Turnover Temperature	T _O		10	25	40	°C
	Turnover Frequency	f _O			f _C		kHz
	Frequency Temperature Coefficient	FTC			0.032		ppm/°C ²
Frequency Aging	Absolute Value during the First Year	fA			<±10		ppm/yr
DC Insulation Resistance between Any Two Terminals				1.0			MΩ
RF Equivalent RLC Model	Motional Resistance	R _M			14.1		Ω
	Motional Inductance	L _M			17.2		μΗ
	Motional Capacitance	C_{M}			2.0		fF
	Shunt Static Capacitance	Co			2.3		pF
Test Fixture Shunt Inductance		L _{TEST}			14.6		nΗ
Lid Symbolization (in addition	to Lot and/or Date Codes)				708, <u>YWW</u>	<u>S</u>	
Standard Reel Quantity	Reel Size 7 Inch			5	00 Pieces / Ro	eel	
	Reel Size 13 Inch			30	000 Pieces / R	teel	




CAUTION: Electrostatic Sensitive Device. Observe precautions for handling. NOTES:


- 1. The design, manufacturing process, and specifications of this device are subject to change.
- 2. US or International patents may apply.


Electrical Connections

The SAW resonator is bidirectional and may be installed with either orientation. The two terminals are interchangeable and unnumbered. The callout NC indicates no internal connection. The NC pads assist with mechanical positioning and stability. External grounding of the NC pads is recommended to help reduce


Pin	Connection
1	NC
2	Terminal
3	NC
4	NC
5	Terminal













Temperature Characteristics

The curve shown accounts for resonator




Characterization Test Circuit

Inductor L_{TEST} is tuned to resonate with the static capacitance, C_O, at F_C.




Power Dissipation Test



Case and Typical PCB Land Dimensions

Ref	mm			Inches		
	Min	Nom	Max	Min	Nom	Max
Α	2.87	3.00	3.13	0.113	0.118	0.123
В	2.87	3.00	3.13	0.113	0.118	0.123
С	1.12	1.25	1.38	0.044	0.049	0.054
D	0.77	0.90	1.03	0.030	0.035	0.040
E	2.67	2.80	2.93	0.105	0.110	0.115
F	1.47	1.60	1.73	0.058	0.063	0.068
G	0.72	0.85	0.98	0.028	0.033	0.038
Н	1.37	1.50	1.63	0.054	0.059	0.064
I	0.47	0.60	0.73	0.019	0.024	0.029
J	1.17	1.30	1.43	0.046	0.051	0.056
K		3.20			0.126	
L		1.70			0.067	
М		1.05			0.041	
N		0.81			0.032	
0		0.38			0.015	

Equivalent RLC Model



Example Application Circuits

Typical Low-Power Transmitter Application


Modulation Input

200k Ω +9VDC C1

(Antenna)

ROXXXXC Bottom View

RF Bypass



Recommended Reflow Profile

- 1. Preheating shall be fixed at 150~180°C for 60~90 seconds.
- 2. Ascending time to preheating temperature 150°C shall be 30 seconds min.
- 3. Heating shall be fixed at 220°C for 50~80 seconds and at 260°C +0/-5°C peak (10 seconds).
- 4. Time: 5 times maximum.

