

# PSA.1S.305.CLLC66

## SUMMARY

#### # Wires

Low voltage



Image is for illustrative purpose only

Series	1S				
Termination type	Female solder				
IP rating	50				
AWG wire size	0.00 - 0.00				
Cable Ø	5.90 - 6.50 mm				
Status	active				
Matching parts	FFA.1S.305.CLAC42				

5

#### Download

Request a quote Catalog

# **TECHNICAL DETAILS**

#### **Mechanics**

	Shell Style/Model	PSA*: Fixed receptacle, nut fixing, cable collet
	Keying	Hermaphroditic keying (half moon insert) with female pin 1
	Housing Material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces
	Weight	14.84 g
Pe	erformance	
	Configuration	15.305 : 2 (0.9 mm) + 3 (0.7 mm) Low Voltage
	Insulator	L: PEEK (UL 94 / V-0/1.5)
	Rated Current	

#### Specifications

Contact Type: Solder Vtest: 1500 V (AC), 2100 V (DC) Vtest: 1500 V (AC), 2100 V (DC)


#### Others


Endurance (Shell): 5000 mating cycles Temp (min / max): -55°C / +250°C

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Humidity (max): <=95% [at 60 deg C /140 F] Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [ 6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >144 hr

### DRAWINGS







#### Dimensions

	А	В	С	E	L	Μ	S1	S2	\$3	e
mm.	14	16	6.2	7.5	40.5	1.5	10.5	8.5	14	M12x1.0
in.	0,55	0,63	0,24	0,30	1,59	0,06	0,41	0,33	0,55	

### **RECOMMENDED BY LEMO**

#### Tools

Spanner wrench:

DCD.1S.ZZZ.PA085

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.