

LQW18CNR39J0Z#

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CNR39J0Z# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=LQW18CNR39J0Z%23

"#" indicates a package specification code.

For Power Choke



< List of part numbers with package codes > LQW18CNR39J0ZB LQW18CNR39J0ZD LQW18CNR39J0ZJ

Applications

Unsuitable	Please he sure to read and comply with		
Unsultable	Please be sure to read and comply with		
Applications	these "Precautions for use."		
Specific	Consumer equipment,Automotive infotainment/comfort equipment,Medical		
	equipment [GHTF A/B/C] except for		
	implant & operation & auto-dispenser		
	equipment,Industrial equipment except		
	for transportation & facility & energy		
	equipment		
	Please refer to Our Website and		
Applications	specifications, etc. for information about		
	the performance, functions, quality,		
	management, and safety required for		
	the above applications, and use		
	Products after confirming the		
	performance and reliability of the actual		
	Product.		


References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)		
1 piece	0.004g	

Appearance & Shape





1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





LQW18CNR39J0Z#

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CNR39J0Z# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=LQW18CNR39J0Z%23

"#" indicates a package specification code.



Specifications

L size	1.6±0.15mm
W size	0.8±0.15mm
T size	0.8±0.15mm
Size code inch (mm)	0603 (1608)
Inductance	390nH±5%
Inductance Test Frequency	10MHz
Rated current (Itemp) (Based on Temperature rise)	620mA
Max. of DC resistance	0.28Ω
Class of magnetic shield	No Shield
Self resonance frequency (min.)	570MHz
Operating Temperature Range(Self-temperature rise is not included)	-40℃ to 125℃
Brand	Murata
Series	LQW18CN_0Z

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Product Search Data Sheet

LQW18CNR39J0Z#

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CNR39J0Z# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=LQW18CNR39J0Z%23

"#" indicates a package specification code.



In operating temperatures exceeding +85°C, derating of current is necessary for this series. Please apply the derating curve shown in the chart according to the operating temperature.

Derating of Rated Current



3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CNR39J0Z# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=LQW18CNR39J0Z%23


"#" indicates a package specification code.


LQW18CNR39J0Z#

Characteristic Data

The charts below may show another part number which shares its characteristics.







4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

