

PHN.2M.310.XLPT

SUMMARY

Wires

Low voltage

10



Image is for illustrative purpose only

Series	2M			
Termination type	Female crimp			
IP rating	68 when mated			
AWG wire size	26.00 - 22.00			
Cable Ø	6.50 - 13.00 mm			
Status	active			
Matching parts	FGN.2M.310.XLBT			

Download

Request a quote Eplan Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model	PH*: Free receptacle with arctic grip and mold stop
Keying	3 keys (beta=165, gamma=30, plug: male contacts, receptacle: female contacts)
Housing Material	Aluminium (nickel plated [SAE AMS QQ N 290], anthracite color) shell and nut, other pieces bronze/brass
Weight	12.77 g
Performance	
Configuration	2M.310 : 10 Low Voltage
Insulator	L: PEEK
Rated Current	8 Amps

Specifications

Contact Type: Crimp Test voltage (kV rms) Contact-contact: 1.8 Test voltage (kV rms) Contact-shell: 1.2

Others


Ρ

Endurance (Shell): 3000 mating cycles Temp (min / max): -20°C / +200°C

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Humidity (max): 21 days at 95% Gunfire vibration: 25 Hz - 2000 Hz, 3 axis (Apache helicopter) Vibration-Sine: 30 g, 3 axes, 12 hr [10 Hz - 2000 Hz] Vibration-Random: 37.8 g rms - 3 axes, 4 hr amb [50 Hz - 2000 Hz] Shock Resistance: 300 g [3 ms] Lighting strike EIA 364-75: 10K amps - 6 times Thermal shock: 5 cycles: -65°C to +150°C EMI Shielding EIA 364-66A: >= 80 dB (1 GHz), >=70 dB (3 GHz), >= 58 dB (6 GHz), >= 40 dB (10 GHz) Salt Spray Corrosion: max. 48 hr

DRAWINGS



Dimensions

	А	В	С	D	F	Lr	Ls	Μ	Р	Х
mm.	18.9	14	17.2	13	15.5	29	29	10.1	5.3	7.1
in.	0,74	0,55	0,68	0,51	0,61	1,14	1,14	0,40	0,21	0,28

RECOMMENDED BY LEMO

Tools

Crimp Tool:DPC.91.701.VCrimp settings:AWG/Selector = 22-24-26/6-5-5Positionner:DCE.91.090.3MVM

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Extractor:

Replacement contact:

EGN.0M.661.ZZM

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.